
TRANSFORMER

Askarel

Inspection & Maintenance Guide

Monsanto



0145675

TOWOLDMON0023606

Table of Contents

SECTION A
TRANSFORMER ASKARELS 1
I. Introduction 1
II. History of Trade Name Types 1
Table I – The Composition of Transformer Askarels 2
III. Interchangeability 2
IV. Table II – Official Transformer Askarel Shipping Specifications 3
V. Ordering Instructions 2
VI. Stability 2
VII. Precautions When Handling Drums, Tank Cars and When Opening Transformers 2
A. Keep Dry During Handling 2
Table III – Handling and Pumping Temperatures 4
B. Use Ordinary Personal Precautions 4
C. Precautions on Opening an Askarel Transformer 5
VIII. Avoid Environmental Pollution 5
1. Labeling Askarel Transformers 6
2. Disposal of Liquid and Solid Wastes 6
3. Conditioning of New or Recycled Askarel .6
4. Teardown of Transformers for Repair or Scrap 7
6. Transformer Disposal 7
IX. Expected Service Life 7
X. General Characteristics of Transformer Askarel Fluid 7
XI. Sampling Transformer Askarel Fluid 8
XII. Evaluation of Askarel Received in New Equipment 8
XIII. Dielectric Breakdown Voltage – Moisture Relationship 9
Table IV – Relation of Dielectric Breakdown Voltage to Amount of Dissolved Water in Askarel and Mineral Oil 9
Table V – Approximate Solubility of Water in Transformer Askarel and Mineral Oil 10
XIV. Turbidity 10
XV. Check Points for Maintaining Askarel Insulation 10
A. General Considerations 10
B. Modern Sealing Procedures 11
C. The Older Sealing Arrangements 12
XVI. Periodic Fluid Inspection and What Checkpoints Mean 12
A. Visual Inspection 13
B. Dielectric Breakdown Voltage 13
XVII. Inspection Checklist 13
XVIII. Contamination in Transformers 14
Table VI – Effect of Common Insulation Materials on Power Factor and Dielectric Strength 14
Table VII – Effect of Common Insulation Materials on Volume Resistivity of Askarel 14
XIX. ASTM Method for Investigating the Compatibility of Transformer Insulation and Construction Materials in Askarels 15
XX. Refining Askarel for Re-Use 15
A. *Filtering Through Dry Blotter Paper* to Remove Moisture and Extraneous Particles 15
Table VIII – Water Removal by Filtering Askarel Through a Paper Press 16
B. Disposal of Solid Wastes 16
C. Solid Insulation Requiring Drying 16
D. Earth Treatment for Maximum Improvement of Power Factor and Volume Resistivity 16
Table IX – Effect of Power *Factor and Volume Resistivity* 17
XXI. Cleaning Arced Transformers 17
XXII. Sampling Askarel 17

SECTION B
ASKAREL FILLED SWITCHES AND TERMINAL CHAMBERS 19
I. Introduction 19
II. Sources of Contamination 19
III. Sealing Switches and Terminal Chambers 20
IV. Askarel Used Under Mild Arcing Conditions .20
V. Maintenance for Askarel Filled Switches 20
VI. Askarel Under Excessive Temperature or Fault Conditions 21

SECTION C
TOXICITY AND SAFE HANDLING 21
I. Inhalation 21
II. Skin Contact 21

SECTION D
ANALYTICAL SERVICES ON TRANSFORMER ASKAREL AVAILABLE FROM MONSANTO 22
Types of Analyses Available: 22
1) Routine Maintenance Check 22
2) Complete Analysis 22
3) Analysis After Earth Refinement 22

SECTION E
APPENDICES 23
Appendix A – Askarel Stability and Composition of Arc Formed Gas 23
Appendix B – Solubility of Gas in Transformer Askarels 23
Appendix C – Effect of Temperature on Dielectric Breakdown Voltage of Askarel 23
Appendix D – Comparison of the Approximate Viscosity in Saybolt Universal Seconds of Transformer Askarels and Mineral Oil 24
Appendix E – The Density of Inerteen 54201 KA 7336-9 and Transformer Pyranol A13B3B-3 24
Appendix F – Thermal Conductivity Values of Transformer Pyranol A13B3B-3 24
Appendix G – Heat Capacity 24
Appendix H – Coefficient of Expansion 24
Appendix I – Fire Resistance 24
Appendix J – Seals, Properties and Procurement 25
Appendix K – Caution Label 25

NOTICE: "Nothing contained herein is to be construed as a recommendation to use any product in conflict with any patent. MONSANTO MAKES NO WARRANTIES AS TO THE FITNESS FOR A PARTICULAR PURPOSE OR MERCHANTABILITY OF ANY PRODUCT REFERRED TO, no guarantee of satisfactory results from reliance upon contained information or recommendations, and disclaims all liability for any resulting loss or damage."

0145676

TOWOLDMON0023607

Section A
Transformer Askarel

I. Introduction

The term "askarel" as defined by IEEE, ASTM and the National Electrical Code generally describes a broad class of fire-resistant* synthetic chlorinated hydrocarbon insulating liquids widely used in transformers, reactors and accessory equipment operated at power frequencies. Askarels of various compositional types are in use. (For the general properties and types see ASTM D-2283.) Under arcing conditions the gases produced, while consisting of predominantly non-combustible hydrogen chloride, can contain varying amounts of combustible gases depending upon the askarel type.

This manual describes the operating characteristics of transformer askarel liquid insulation as manufactured by Monsanto and how it differs from mineral oil. Appropriate handling and disposal procedures for both scrap askarel liquid and impregnated solid materials are given in accordance with the guidelines recommended by the American National Standards Institute.

The information is based on facts gathered by Monsanto over 40 years as a producer of askarel, plus knowledge gained from the experience of transformer manufacturers and users. This guide outlines the maintenance required for askarel fluid in "modern" transformers and offers suggestions for sealing and maintaining askarel in old units. By following this guide, we believe users will obtain maximum service from askarel insulation with a reasonable minimum of maintenance. If questions arise relating to the designing and building of transformers, these should be referred to regular transformer suppliers.

Monsanto gratefully acknowledges the assistance, guidance and the contributions of certain data by the following:

Edward C. Raab – General Electric
Dr. T. K. Sloat – Westinghouse Electric

II. History of Trade Name Types

Askarel is the generic name for the fire-resistant liquid insulation and coolant first used by General Electric Company in 1932 for their Pyranol® brand name fire-resistant transformers. Westinghouse Electric Corporation uses their brand name, Inerteen.®

Whatever the trademarked brand, the askarel contains chlorinated biphenyl – one of the best liquid insulations developed by science. This inert material is chemically stable, fire-resistant, heat stable, non-corrosive, and has high dielectric strength under the operating conditions encountered in transformers.

In addition to manufacturing Aroclor® (chlorinated biphenyl), Monsanto also mixes this basic fluid with chlorobenzenes to produce and presently [illegible] Aroclor and Pyranol blends described in [illegible]

[illegible] askarels [illegible] and are more difficult to [illegible] corresponding conventional [illegible] askarel materials will not burn. [illegible] ASKAREL FLUIDS are [illegible] equipment."

*Underwriters Laboratories, Inc. Standard No. 1446

®Registered trademark of Westinghouse Electric Corporation

®Registered trademark of Monsanto Company

TOWOLDMON0023608

Table I
The Composition of Typical Transformer Askarels

	Method ASTM D2283		
	Type D	Type E	Type G
Trade Names	Inerteen 70-30	Inerteen 100-42	Pyranol A13B3B3
Ingredients (% by wt.)			
Aroclor® 1254, chlorinated biphenyl (54% chlorine by weight)	70	–	60
Aroclor® 1242, chlorinated biphenyl (42% chlorine by weight)	–	100	–
Trichlorobenzene	30	–	40
Phenoxypropene oxide scavenger	0.18 to 0.22	0.18 to 0.22	–
Diepoxide scavenger	–	–	0.115 to 0.135

ASTM Method D-2283, titled *"Chlorinated Aromatic Hydrocarbons (Askarels) For Transformers"*, also lists the composition of all transformer askarels used at various times since 1932.

Monsanto manufactures similar transformer askarel fluids in England where the trade name Pyrocior is used.

III. Interchangeability

In general all transformer askarels are interchangeable. However, it is suggested that the transformer manufacturer be consulted prior to mixing in significant proportions or total substitution.

IV. Transformer Askarel Specifications

Specifications for the three common transformer askarel fluids are shown in Table II.

V. Ordering Instructions

Monsanto's current policy is to sell askarel transformer fluids only to transformer manufacturers. Questions related to these fluids should contact the manufacturers of the transformers and not Monsanto. The transformer name plate usually identifies the transformer maker and usually gives sufficient data to identify the specific askarel fluids used.

VI. Contamination

Askarel insulation must never be mixed with mineral oil. Over two percent of mineral oil by volume in askarel begins to lower its fire resistance.

In modern transformers, the principal "enemy" of askarel is contamination by water. Keeping askarel water-free will insure long-time service.

Askarel is heavier than water. If water is put into askarel insulation, only a tiny amount (approximately 1% part) dissolves – the rest floats on top. Askarel is very insoluble in water, only about 200 parts per billion of askarel dissolve in water at normal temperatures.

VII. Precautions When Handling Drums, Tank Cars, and When Opening Transformers

The following are significant precautions:

A. Keep Dry During Handling
In handling, storing, sampling and inspecting askarel – and in

0145678

TOWOLDMON0023609

Table II

Transformer Askarel Specifications (New Fluid)

Specification Properties[1]	General Electric Co. Transformer Pyranol A13835-3 ASTM D2283 Type C	Westinghouse Transformer Inerteen 70-30* ASTM D2283 Type D	Westinghouse Transformer Inerteen 100-42* ASTM D2283 Type E
Color, APHA	150 max.	150 max.	60 max.
Condition	Clear	Clear	Clear
Water content, ppm (ASTM D1533-60)	130 max.	30 max.	35 max.
Acidity, mg KOH/g (ASTM D974-55)	0.014 max.	0.014 max.	0.01 max.
Dielectric Strength, 25°C, 0.1 in. gap (ASTM D877-49)	35 KV. min.	35 KV. min.	35 KV, min.
Dielectric Constant, 100°C, 60 Hz (ASTM D924-49)	4.2 to 4.6	4.2 to 4.5	4.7 to 4.9
Volume Resistivity, 100°C, 500 volts DC 0.1 inch gap, 10^{12} ohm-cm (ASTM D1169)	100	100	100
Inorganic chlorides, ppm (ASTM D1821 and G.E. Method 640C-18)	0.10 max.	0.10 max.	0.05 max.
Refractive index, 25°C (ASTM D1807)	1.6140 to 1.6120	1.6153 to 1.6173	1.6240 to 1.6260
Viscosity at 37.8°C (ASTM D88-56) Saybolt Universal Seconds	44 to 48	56 to 63	82 to 92
Pour Point °C (ASTM D 97-57)	-30 or lower	-30 or lower	-17 or lower
Specific gravity 25/15.5°C (ASTM D1810)	1.495 to 1.510	1.518 to 1.528	1.381 to 1.392
Burn point (ASTM D92)	None to boiling	None to boiling	None to boiling
Distillation range (ASTM D 20-56) corrected for stem and barometric pressure	1st drop 200°C min. 40% max. below 270°C 90% 379 to 394	1st drop 200°C min. 35% below 270°C 90% 379 to 394	10% 325°C min. 90% 360 max.
Halogen Content	60 to 62%	55.6% min.	43 ± 0.5%
Compatibility with Aluminum	After heating with aluminum for 6 hrs. at 200 to 220°C, the aluminum must not be corroded as determined by weight inspection and the askarel should meet the following specifications:		
Color, APHA	200 max.	200 max.	200 max.
Acidity, mg KOH/g	0.014 max.	0.014 max.	0.01 max.
Inorganic chlorides ppm	0.45 max.	2.0 max.	0.15 max.
Condition	Clear	Clear	Clear
Scavenger content	0.115 to 0.135% Diepoxide	0.18 to 0.22% phenoxypropene oxide	0.18 to 0.22% phenoxypropene oxide
Typical Properties[2]			
Coefficient of Thermal Expansion (ASTM D1903) $cm^3/cm^3/°C$	0.0007	0.0007	0.00065
Are formed gases	Askarels of various compositional types are used. Under arcing conditions the gases produced, while consisting predominantly of non-combustible hydrogen chloride, can include varying amounts of combustible gases depending upon the askarel type. Insulation systems incorporating these askarels and cellulosic or other organic materials may, when arced, produce gaseous mixtures which are moderately flammable. As a precaution, such gases should be removed from the askarel by bubbling dry nitrogen through the askarel and flushing the gas space with dry nitrogen before any work is performed on the apparatus.		

*Westinghouse uses their private number Inerteen 54201KA for Inerteen 70-30 and their private number Inerteen 54201CM for Inerteen 100-42.

[1]These quantities are final sales specifications only to the extent that they coincide with Monsanto's published specifications.

[2]This data is based upon samples tested in the laboratory and is not guaranteed for all samples. Write us for complete sales specifications for Askarel fluids.

3

0145679

TOWOLDMON0023610

...ed askarel transformers ... with a dry, inert gas to guard ... askarel insulation from exposure to high humidity and ... moisture contamination. Keep ... 5 or 55 gallon drums of askarel ... dry, lay stored drums on their sides with the bung at the highest point from floor to keep water off the drum head (water can be sucked into the askarel by the drum "breathing"). This precaution is not necessary when drums are stored indoors, which is the preferred place for storage.

To avoid leakage the drums used for askarel are of heavy construction. Sixteen gauge metal is used, with special rim seal end bung construction. The drums should be drained as completely as possible and then flushed twice with kerosene type solvent to remove all of the askarel. Accumulated liquids and washings should be collected and should be incinerated at high temperatures, e.g., about 2000°F to destroy the polychlorinated biphenyls (PCBs). See Section A, VIII).

Tank cars used to transport askarel are in exclusive service and not used interchangeably for other products. All cars must be unloaded through the top dome fitting either by pumping or with controlled pressure using dry air or dry nitrogen. If nitrogen has been used for unloading it is necessary to advise the shipper so that when the car returns the nitrogen can be replaced with dry air before any one may enter the car. If the car is to be unloaded by pumping it will be necessary to use a dryer on the air intake line to remove moisture.

All tank cars are fitted with steam coils which are available for unloading under extreme low temperature conditions.

Convenient handling and pumping temperatures are given in Table III.

B. Use Ordinary Personal Precautions

Transformer askarel has been ... handled ... used for over 40 years. It can be handled safely ... ordinary ... precautions. If ... accidentally spilled on ... , no ... action will occur. However, liquid askarel ... eye ... section ... to skin ...


Table III

Handling and Pumping Temperatures

Product	...
Pyranol A1383S	... 55
Inerteen 70-30	... 55
Inerteen 100-42	... 75


... thinner) on the fats and oils of the skin and prolonged contact ... may lead to drying and chapping of ...

... case of contact with the skin wash ... and water. Remove and ... clean saturated clothing. Cleanse ... with rag, oily dust and ... dry clay. Eye contact ... irritation but no ... permanent damage to tissue ... flush with ... large amounts of water ... to relieve irritation ... solution as well ...



0145680

TOWOLDMON0023611



...with an organic coating material approved by the U.S. Bureau ...

...tion. Do not use ... in ... ...

...ation of various ... are used. Under arcing ...through the gas. Products ... consisting of predominantly ... non-combustible hydrogen ... and varying amounts of ... ...

...ulation systems ... ... and cellulosic or ... organic materials may ... ... produce gaseous ... mixtures which are ... ... As a precaution, such ... gases should be removed ... from the system by bubbling dry ... nitrogen through the system and ... the gas space with dry ... nitrogen before any work is performed on the apparatus.

The Institute of Electrical and Electronic Engineers Guide ... (March 1974) gives ... instructions and guidance ... *Recognized and Minimized Electrical Hazard in Equip-* ... This guide is available ... from the Institute of Electrical & Elec- ... Engineers, Inc., 345 E. 47th ... New York, New York ... We recommend this ... ... transformers refer to this ... document.

VIII. Avoid Environmental Pollution

...chlorinated askarel contain ... biphenyls (PCBs) which ... used in the ... elsewhere over the past 40 ... many industrial ... applications. During the past ... years evidence has ... indicate that PCBs are widely ... throughout ... and that they can have adverse ... ecological and toxicological ...

... Environmental Task Force on ... 1972 report titled, ... ", recommended ... ...

... technical information ... Virginia 22151:

... *Disposal of Capacitor ... Polychlorinated* ... from the American ... 430 Broadway, New ...

... committees are: ...

Scope: ... ... maintenance and disposal of ... ... in electrical equipment.

Objectives: ... ... and advice for Federal, ... concerned. ... ... disposal facilities and ... ... States participation in ... ...

Composition: ... ... ANSI committee ... Association, Electronic ... trial and Electronic ... and Materials; Electric ... Ballast Manufacturers ... Association; Environmental Protection Agency; Office of Environmental Affairs, General Services Administration; National

TOWOLDMON0023612

[illegible] Environmental Protection Agency, Federal Power Commission, Department of Transportation, Water Pollution Control Federation, Food and Drug Administration, National Fire Protection Association, Underwriters Laboratories and several sections of the U.S. Department of Interior.

The following are pertinent excerpts taken from the ANSI Guidelines for askarel transformers:

1. LABELING ASKAREL TRANSFORMERS (Pg. 16)

4.2.2.1 New Transformers. All new transformers that contain PCBs shall have a label of adequate durability, permanently and prominently attached to the tank by the manufacturer, given adequate warning and instructions. A suggested label includes the following:

CAUTION: The insulating liquid in this transformer contains polychlorinated biphenyls (PCBs). Care should be taken to prevent entry into the environment. In case of malfunction or leaks, consult the instruction manual or the manufacturer.

4.2.2.2 In-Service Transformers. The transformer manufacturer should make available suitable labels with a similar warning as shown in 4.2.2.1 for use on existing transformers.

2. DISPOSAL OF LIQUID AND SOLID WASTES (Pg. 16)

4.1.6.5.1 General. Disposal of askarels and askarel-soaked materials should be accomplished by means in which there is no significant release of askarel to the environment. At present, disposal is accomplished by carefully controlled incineration of liquids and soaked software, and by controlled landfill burial of apparatus and other hardware from which askarel has been previously drained and washed.

Present knowledge indicates that proper incineration must involve a suitable balance between dwell time and temperature in the incineration plus oxygen availability and, finally, suitable scrubbers to remove the HCl that will be formed, for example, 2-second dwell time at 2000°F and 3% excess oxygen in stack gas or 1.5-second dwell time at 2700°F and 3% oxygen in stack gas.

These facilities should meet the applicable requirements of the state in which they are located and should control effluents within the limits set forth in this standard.


Controlled landfill or deep well disposal can be used where permitted by federal, state and local regulations.

The ANSI Guide lists [illegible] facilities that conform with the above requirements. Westinghouse has such an incinerator at the W. G. Krummrich Plant, Department 831, Sauget, Illinois 62201, where arrangements can be made for scrap askarel liquid disposal for a modest fee. For disposal of solid scrap a controlled dry land fill can be used where permitted by Federal, State and local regulations.

3. CONDITIONING OF NEW OR RECYCLED ASKAREL (Pg. 16)


4.2.1.3.1 Askarel Conditioning Equipment. The conditioning unit should be located either in the storage tank area or in the main transformer manufacturing area for filling with askarel.

4.2.1.3.2 Fuller's Earth. Conditioning of new askarel or recycled askarel requires fuller's earth treatment. The spent fuller's earth in cartridges or bags, when replaced, should be allowed to drain thoroughly over drip pans to remove as much liquid askarel as possible. The cartridge units of steel mesh construction should be placed in the "STEEL CONTAMINATED WITH ASKAREL" container for disposition. Cloth bags filled with fuller's earth should be placed in the "SCRAP BURNABLE ASKAREL WASTE" container for disposition.



0145682

TOWOLDMON0023613



4.2.1.4.2 TEARDOWN OF TRANSFORMERS FOR REPAIR OR SCRAP (Pg. 16)

4.2.1.4.2 Drain all askarel from the unit either into a holding tank or reuse or into the drum labeled "SCRAP ASKAREL" for disposition, and then allow sufficient time for all of the askarel to drain from the core and coils.

4.2.1.4.3 Remove the core and coil assembly from the transformer. Sufficient absorbent material should be placed on the floor to absorb any askarel fluid that still drips from the transformer.

4.2.1.4.3 Place all materials in the appropriate salvage containers during the dismantling for later disposition.

4.2.1.4.4 All used materials, including rags, sawdust, tape, etc., regardless of quantity, shall be put into the appropriate containers for disposition.

5. TRANSFORMER DISPOSAL (Pg. 17)

4.2.3.6 The ultimate disposal of an askarel-filled transformer may be accomplished in either of two ways:

(1) Complete drainage and dismantling with the proper disposal of the askarel and askarel-soaked components as described in 4.1.6.

(2) Disposition of askarel transformers by means of junk or scrap dealers. This should be avoided unless a transformer is first drained, followed by soaking the interior with a suitable solvent. Accumulated liquids and washings are to be disposed of as described in 4.1.6.

IX. Expected Service Life

Manufacturers indicate that properly designed and installed askarel transformers are expected to give trouble-free service for at least 30 years. Since their introduction in 1932, the manufacturers report finding the overall failure rate to be less than 0.5% for all units under usual and service conditions. The Edison Electric Institute's report 1964 (988) on their member utilities publishes the failure rate for askarel transformers as 0.13 per hundred banks per year.

[illegible] Clark, who installed transformer askarels at the General Electric Company in the early 1930s, made the highly pertinent statement based on his many years of experience with G.E. Pyranol [illegible] transformers to [illegible]

"The important thing is to keep them dry – otherwise leave them alone."

These words of wisdom [illegible] especially applicable in more recent years when welding and not [illegible] became the main method of sealing askarel transformers. These units are sold with the understanding that the fluid is in a normally hermetically closed system.

X. General Characteristics of Transformer Askarel Fluid

Application of the following characteristics, as given in the IEEE Guide, leads to understanding the reasons for selecting dielectric breakdown voltage and moisture as the prime practical tests to judge the quality of transformer askarel fluid. Also, due to these characteristics the power factor of transformer askarel will be normally much higher than the corresponding values for mineral oil.

In comparison to mineral insulating oil, askarel is a relatively polar [illegible] its molecules are dipoles, free to rotate around their axes and respective to orientation by electrical forces. Askarel also exhibits much higher dielectric constant and capacitance than insulating oil, and these differences must be kept in mind when interpreting electrical [illegible]


Because it is relatively polar, and possesses high solvency power, askarel is much more electrically sensitive than mineral oil to traces of extraneous soluble polar materials, and consequently the choice of

TOWOLDMON0023614



0145684

TOWOLDMON0023615



...degree of the degree of extraneous soluble polar materials present.

Recognizing the desirability of a wide range of power factors being acceptable for askarel electrical equipment, it is difficult to establish a realistic limit which would be acceptable to both suppliers and users for all applications. However, at a broad guide, power factors up to about 10% at 25 degrees C and 60 cycles per second (hertz) do not in general indicate any abnormal contamination provided that the other parts (e.g. water content, dielectric breakdown voltage, etc.) are met. Much higher power factors may indicate excessive contamination or the misapplication of the solid materials used in manufacture in contact with the askarel and should be investigated.

XIII. Dielectric Breakdown Voltage – Moisture Relationship

The dielectric breakdown voltage of askarel is highly sensitive to excess moisture, not sensitive to ordinary dissolved polar materials. While the dielectric breakdown voltage can also be lowered by severe arcing, askarel turns noticeably black or has particles of sooty carbon floating in it if arcing has occurred. Then the transformer should be repaired and the askarel replaced.

If the dielectric breakdown voltage is checked periodically and decreases significantly, this indicates moisture pick-up, arcing, or both. When the dielectric breakdown voltage has dropped to 26 KV or less, an analysis for water is necessary. If water is found in excess of 40 ppm at room temperature, the source should be located and corrections made.

When the moisture content approaches 125 ppm (saturation level at room temperature), the dielectric breakdown voltage of askarel drops below the value required for efficient insulating. The moisture content should not be allowed to rise over 60 ppm sampled at operating temperature. If the moisture content is found to be in a satisfactory range and the dielectric breakdown voltage is low, the transformer insulating liquid should be examined.

Figure 1 shows the relationship of dielectric breakdown voltage vs. moisture content for askarel and mineral oil at approximate water solubility limits at room temperature.

Table IV
Variation of Dielectric Breakdown Voltage to Amount of Dissolved Water in Askarel and Mineral Oil

Water Content (PPM)	Breakdown Voltage (ASTM D877) Askarel	Mineral Oil
0	70 KV	50 KV
20	55	39
40	47	30
60	40	26
80	34	22
110	30	6

0145685

TOWOLDMON0023616

Table V

Approximate Solubility of Water in Transformer Askarel and Mineral Oil

°C	°F	Amount of Water (PPM) Dissolved: Askarel	Mineral Oil
-30	-22	8	8
-20	-4	16	10
-10	14	28	13
0	32	41	20
10	50	65	33
20	68	94	58
30	86	128	85
40	104	170	130

XIV. Turbidity

. . . may be the visual sign of undissolved water, or may indicate dirt. Cloudiness may also result from cold precipitation of tin tetraphenyl "scavenger" that was used in the earlier Pyranol transformers. This scavenger begins to come out of solution around 15°F above zero. To redissolve it requires heating to 150-200°F and agitation.

High dielectric breakdown voltage will quickly indicate that any turbidity present is not moisture; that the insulating efficiency of the askarel is still excellent. However, if the dielectric strength is below 26 KV, moisture should be determined, using the Karl Fischer method (ASTM D1533-60).

The dielectric breakdown voltage test for askarel serves primarily as an indicator for moisture. It is by far the most important maintenance test for transformer askarel.

XV. Check Points for Maintaining Askarel Insulation

A. General Considerations:


Modern askarel transformers with welded construction of silicone or Viton* gaskets (hand hole cover, switch and terminal compartment covers) and with properly constructed bushings require little maintenance. With properly constructed transformers, annual or semi-annual visual inspection and dielectric breakdown voltage test of the askarel fluid should suffice for routine maintenance checking over many years of service.

However, many askarel units were installed in the early 1930s – before the development of some of the better modern gasketing materials and before improved designs were developed for sealing out moisture. Such early units should be, and can be, modernized. Leaky or deteriorated gaskets should be replaced. If the askarel has become contaminated, it should be reconditioned. At the same time, a general clean-up of the unit and possible refinishing may be desirable.

If it is not convenient to take an old transformer out of service for general repairs, leaky gaskets can be sealed temporarily by painting over the leaky area with epoxy cement.

A survey of users indicates a good number of early-built askarel transformers (over 20 years old) are kept in continuous service in critical installations by the following strict attempt at modernization:

The operating units are supplied with compound pressure gauges for reading pressure 15 lb. and below atmospheric. Positive



*Trademark of E. I. DuPont DeNemours & Company, Inc.

0145686

TOWOLDMON0023617

...ure is maintained on the shell by introducing nitrogen at 2 to ... above atmospheric. Regular workmen in the area daily ... temperature and pressure. If a sudden pressure drop is ... more nitrogen is introduced and the gaskets are checked for ... with soap solution. Leaks are sealed by applying epoxy ...

b. Modern Sealing Procedures:

Transformer purchasers should specify the following modern techniques for sealing.

1. Welding Construction: Cooling radiator connections, switch and terminal housings, instrument connections, etc. should be welded.

2. Bushing Connections: A number of bushings have been developed to obtain a proper seal for the electrical connection through the tank wall. They are classified as follows:

   a) Welded Type - (Bushing flange welded to tank wall)
      a. Cast resin bushing with a molded seal to the bushing stud and external stainless steel or copper flanges.
      b. Rolled flange bushing with the metal to porcelain seal at the cap and flange made by being rolled into grooves in the porcelain over silicone rubber rings. The seal between the cap and stud is made by welding.
      c. Porcelain or glass bushings with metal to glass or metal to porcelain seal.
   b) Bolted Type - (Bolted to tank wall)
      a. Cast resin bushings with either cast or metal flanges containing recessed gasket grooves.
      b. Porcelain or glass bushings with flanges containing recessed grooves or gasket stop.

...ket to body be either of rectangular or circular cross-section, ... thick. Bushings with recessed grooves are suitable ... cork-nitrile rubber combinations or nitrile rubber ... gasket materials such as silicone or Viton.


...Side Connections: When it is possible to weld, small ... connection seals should be made with Flexitallic" ... steel rings. The surfaces must be machined and ... The fillet between the steel laminations of the ... ring should be either silicone or Viton.

...ge for Hand-Hole Covers: Modern design specified ... gaskets. Such gaskets must be retained in a groove. ... groove preferably is machined into the flange or cover. ... can also be formed by welding concentric steel ... to the flange or the cover. Generally the gaskets should ... to 1/4 in. thick for covers, depending on the depth ... groove or stop. A rectangular cross-section is usually ...

...material around the Dow Corning No. 50 ... or equivalent. This is a low compression set ... seal. Such compression is ... groove or stop to ... the gasket is ...


... contributes to ... gasket fluid ... chemically stable and ...

TOWOLDMON0023618



0145688

TOWOLDMON0023619



Askarel is a clear, light yellow liquid. After long-term use this color may gradually change to light brown. The fluid should remain clear and free from turbidity or cloudiness.

Any color other than of a light, red or blue cast indicates extraction of coloring materials from the solid insulation. If, in addition, a dark color pickup is noted, check the complete range of electrical characteristics and notify the transformer maker. Discoloration of the askarel may indicate an arcing condition. Other color changes alone are not danger signals since the dielectric breakdown voltage is not likely to be impaired.

3. Dielectric Breakdown Voltage

If the dielectric breakdown voltage has decreased significantly from the last inspection, or if it has gradually decreased below 26 KV range for 25 C., RUN A CHECK FOR MOISTURE. Use ASTM D1533 (Karl Fischer Method).

The dielectric breakdown voltage of askarel is the major indicator of the continued efficiency of your liquid insulation. Besides the visual inspection of color, dielectric breakdown voltage is the only test necessary to carry on a routine basis. Well-sealed askarel transformers have service records of 25 to 30 years on the original askarel.

XVII. Inspection Checklist

1. If askarel is clear, even though darkened to light brown, has no sediment or turbidity and dielectric breakdown voltage over 26 KV – give it the inspection "OK".

2. If askarel is clear, but has taken color of blue, green, red . . . it is extracting color from internal materials. This is not, of itself, an operating hazard unless the dielectric breakdown voltage stays over 26 Kv and moisture is running low. However, this rare occurrence should be reported to the manufacturer of the transformer. Color changes are not danger signals since the dielectric breakdown voltage is not likely to be impaired. However, when sampling [illegible] to avoid getting color into the [illegible] must be inside or outside of the sample [illegible].

3. If the dielectric breakdown voltage is found to be above 70 parts per million (ppm) water, drying should be done at once. Readings between 60 and 70 ppm should be watched, particularly on outdoor installations.

4. If askarel is clear, but dielectric breakdown voltage drops to 22 or below, and moisture reads over 80 ppm when sampled at operating temperature, the askarel is ready for simple reconditioning. If data indicates that the saturation level (about 125 ppm at room temperature) is approached, a thorough inspection should be made for water droplets in the transformer tank, and even for "globules" of water clinging to the askarel surface. If found, the transformer manufacturer should be consulted for reconditioning both the transformer and the fluid.

5. If askarel is dark brown or black, or black particles of carbon are seen, and dielectric breakdown is low, . . . the askarel has been broken down by arcing. The unit is overheated and should be removed and reconditioned. (Refer to ANSI Committee C107 report on *Effects of Use on Askarel and Askarel-Soaked Materials*, 345 East 47th Street, New York, New York 10018.)

[illegible] inspection tests appear, but of the [illegible] appearance and test values is [illegible] your transformer supplier for a complete [illegible].

Whenever a sample is to be shipped to Monsanto, please follow the directions shown under "SAMPLING ASKAREL".

TOWOLDMON0023620

VII. Contamination in Transformers

Moisture, particularly water and acid decomposition products are known to be serious contaminating influences on transformer askarel.

The power factor test normally used for the detection of contamination in *mineral oil filled* transformers is of little use for this purpose in askarel filled transformers, due to the extreme effect of extraneous soluble polar materials. This increase in power factor as illustrated in Table VI has no adverse effect on dielectric breakdown voltage.

Table VI
Effect of Common Insulation Materials on Power Factor and Dielectric Strength
(Heat Aged 96 Hours in Askarel at 100°C.)

Material Immersed	Askarel After Exposure: Power Factor, Percent at 60 Cyc., 100°C	Askarel After Exposure: Dielectric Strength, 25°C
None (control)	1.0	35 KV
Black varnished cloth	85.0	42
Copper	1.5	40
Pressboard	2.0	37
Manila paper	1.5	39
Phenol formaldehyde resin	1.6	41
Shellac	6.0	36
Iron	5.0	39
Synthetic rubber	70.0	38

Similarly, trace contaminants from commonly used construction materials can lower the volume resistivity of askarel, without affecting its dielectric breakdown voltage. This is shown in Table VII.

Table VII
Effect of Common Insulation Materials on Volume Resistivity of Askarel

Sample	Volume Resistivity x 10⁹ ohm-cm at 100°C, 500 Volts DC, 0.1" gap
1. New askarel before heat aging	2,000
2. New askarel after heat aging 96 hrs. at 100°C	1,900
3. After heat aging with 1 sq. inch of material per 100 cc. askarel:	
a. Phenolic resin tap changer barrier	1,200
b. Paper	750
c. Grade A pressboard (tan)	500
d. Grade A pressboard (gray)	480
e. Grade A pressboard laminated strip	400
f. Cotton wrapping	300
g. Glyptal 1276 cement, cured 48 hrs. at 110°C	100


While trace contamination easily lowers volume resistivity from high levels, it is important to note that heavy contamination (as when askarel does not lower the resistivity below a value of 10⁹ ohm-cm at 100°C

The difference between [illegible] mineral oil in this respect can be [illegible]

[illegible] volume resistivity [illegible]

[illegible] breakdown chemically [illegible]

[illegible] NOT CAUSE [illegible] insulation unless the dielectric [illegible] moisture content is also



0145690

TOWOLDMON0023621

Manufacturers of askarel type transformers point out that it is quite well known that askarel transformers with initial power factor of the askarel fluid in excess of 50% at room temperature and 60 Hz are giving satisfactory service life. However, there needs to be assurance that both dielectric breakdown voltage and moisture are at satisfactory levels and do not show adverse trends.

XIX. ASTM D3255 Method For Investigating The Compatibility of Transformer Insulation and Construction Materials in Askarels

This method uses the change of electrical and/or chemical characteristics of transformer askarel resulting from its controlled exposure to insulation and construction materials, in order to evaluate their immediate major "contamination" effect on the askarel fluid. Delayed or long time contamination effects may not be detected.

The method also utilizes various physical tests on the insulation and construction materials after controlled exposure to the askarel to determine the compatibility of these materials with transformer askarel.

Properly proportioned specimens of the insulation or structural materials are immersed in refined askarel for 168 hours at 100 ± 1°C in a forced draft oven. Changes in electrical and chemical properties of the transformer askarel are compared against a control sample of the askarel treated in the same manner, in absence of the test specimens.

Dissipation factor (ASTM D 924) change is one of the criteria used. The askarel fluid is refined by absorptive treatment to a dissipation factor level of 0.05 max. at 100°C and 60 Hz and 0.01 max. at 25°C and 60 Hz. Corresponding values of the askarel fluid after heating 168 hours at 100°C in absence of a test specimen are 0.075 and 0.02 respectively. The maximum dissipation factor levels suggested for the askarel after heating in presence of the test specimen are 0.20 at 100°C and 60 Hz and 0.04 at 25°C and 60 Hz.

XX. Refining Askarel for Reuse

A. Filtering Through Dry Filter Paper to Remove Moisture and Extraneous Particles

Most operators prefer portable refining apparatus, such as a plate press fitted with a dolly, available from Sperkler, Mundelein, Illinois or General Electric Company, Pittsfield, Massachusetts; or the similar Shriver filter, now available from Industrial Filter Corporation, Laberton, Indiana. Filter paper liners for the plate press are available from Carl Schleicher and Schuell Company, Keene, New Hampshire and manufacturers of filter presses listed above.

The filter paper must be dried immediately before use. For best results, spread the paper for maximum surface exposure in a hot air circulating oven and heat it for 4 to 6 hours at 110°C.

Circulate the askarel (but not over 40°C) through the filter fitted with the dry paper liners.

After filtration the dielectric breakdown voltage of the askarel should be 35 KV minimum.

PRECAUTIONS

1. Filtering should not be done when the relative humidity exceeds 75%.
2. Any flexible hoses and gaskets of the refining equipment should be lined with by-pass or materials that will not be softened by contact with askarel fluid. (Materials lined with Silicone, Viton A, Teflon* or flexible metal materials are suitable.)

*Trademark of E. I. DuPont DeNemours & Company, Inc.


0145691

TOWOLDMON0023622

TABLE VIII

Guide to Rate of Dissolved Water Removal By Filtering Askarel Through a Paper Press

Passes Through Paper Press	Water in Askarel PPM
0	116
1	56
2	33
3	18
4	12
5	10
6	10



0145692

TOWOLDMON0023623

Table IX

Approximate Relationship Showing the Insignificant Effect of Power Factor and Volume Resistivity on Dielectric Breakdown Voltage of Transformer Askarel

Power Factor at 60 cycs. 100°C	Power Factor at 60 cycs. 25°C	Volume Resistivity ohm-cm at 100°C, 500 Volts DC, 0.1" gap	Breakdown Voltage 25°C, 0.1" gap
3%	0.06%	1500	35 KV
5%	0.1%	500	35
15%	0.7%	100	35
20-25%	2.0%	60-70	35
40-50%		25	35

XXI. Cleaning Arced Transformers

If a unit has arced so that the askarel is no longer fit for use, a thorough cleaning of the unit is necessary before refilling with new askarel insulation and returning it to service. Follow this procedure insuring care is taken to prevent any loss of liquid askarel to effluent streams.

A. Drain out all dark, carbon-contaminated askarel. Arrange to have the scrap fluid incinerated under proper conditions. (See ANSI Committee C107 report.)

B. Carefully brush carbon deposits from internal parts and insulation, using a soft bristle brush, making sure that insulation is not damaged.

C. Flush thoroughly with new askarel — *not* an oil, *not* a cleaning solvent.

D. Flush a second time with new askarel; drain; then fill to the proper level with new askarel.

E. Energize transformer at rated voltage for 24 to 48 hours; then circulate unit through a filter (running it to the unit drained and refilled).

XXII. Sampling Askarel

Take a sample at or near the top of the liquid surface as possible. Many use a special sampling tube consisting of a bottle or sampling tube near the surface of the askarel and connected by a flexible tubing to a point near the bottom. If additional sampling valve connections are contrived on the tank for easier sampling, make the valves of clean glass, stainless steel, aluminum or tin foil. Use Viton and Teflon tubing for flexible type.

Use NEW containers for the askarel sample. A new and thoroughly sun-dried, small-mouth dark glass bottle fitted with a Bakelite** screw cap with aluminum foil cap liner is recommended for quick, on-site testing. (If complete analysis is to be made, a 5-pint size sample is required.)

Be sure that the new bottle has been stored open to collect dust or moisture. Rinse the sample bottle and cap lining two or three times with askarel from the transformer from which it is to be taken. Fill promptly and cap tightly. Label with date used. If sample is to be stored indefinitely, paint the cap with paraffin or wax or wrap clear glass with aluminum foil.

Select a dry day for sampling. Sample insulation on a warm, moist day when humidity [illegible]

This assures that no moisture will be [illegible] established and corrections made. Minor severe arcing [illegible] are usually necessary and the unit rebuilt. This procedure can be applied for flushing out the repaired units.

**Trademark of Union Carbide Corporation


TOWOLDMON0023624

8. Make sure that the askarel is at least as warm as the surrounding air. (Cold liquids can condense moisture from humid air.)

C. When sampling askarel from transformers, it is best to take the sample when the unit is warm and operating at average or maximum load, especially for a check on moisture as reflected by a dielectric breakdown voltage test. Sampling the warm askarel more truly represents its condition during operation.

Experience shows that water will migrate from a transformer's solid insulation to the askarel liquid and vice versa, depending on temperature. Therefore, when the transformer is hot, the moisture is most likely to be found in the liquid. This accounts largely for periodic variations in dielectric breakdown voltage. For example, a relatively high dielectric breakdown voltage may be found during winter months and a relatively low dielectric breakdown voltage during the summer months on samples taken from the same unit.

When testing has been completed, the remainder of the fluid sample should be destroyed by high temperature incineration described in Section VIII.



0145694

TOWOLDMON0023625

Section B
Askarel Filled Switches and Terminal Chambers

I. Introduction

High voltage leads are usually connected to askarel or mineral oil-filled network transformers and power centers through terminal chambers and switches. In some cases terminal chambers are not used, and the high voltage leads are connected directly to the switch terminals. They may be filled with either askarel or mineral oil. Switches are usually rotary or drum type fitted with a revolving block and porcelain unit as the principal element arranged for three-phase service.

Askarel transformers with attached switches have been in use for about 30 years. When they were first introduced, the availability of insulating and gasketing materials was rather limited and even the best materials at the time had no service history. As a result, inadequate gasketing materials such as cork-nitrile rubber, and nitrile rubber-and-cork particles were used. While satisfactory for a limited period of time, these materials cannot be depended upon for the expected long life of the equipment.

The terminal chamber is usually above or below the switch compartment and separated by a steel wall through which the bushings are inserted. When bushings are properly selected and correctly installed, there is no leakage from one compartment to the other. With poor bushing seals and the terminal chamber above the switch, potting compounds or cable oil can seep into the askarel. When the terminal chamber is below the switch, askarel can drain into the terminal chamber.

II. Sources of Contamination

There are three possible sources of contamination for askarel in switches and terminal chambers; they rank in this order of frequency: (1) water entering through poor gaskets; (2) decomposition products from arcing when switch is used to break magnetizing current; (3) entrance of petroleum or cable compounds through leaky bushing seals.

Unlike an askarel transformer, where the amount of contaminant is likely to be very small (possibly only trace amounts) in relation to the volume of askarel fluid, with switches or terminal chambers with faulty seals, the amount of contamination can be relatively large.

Experience has shown that, based on the number of installed askarel-switch units, the percentage of failures is extremely small. When investigated, it has been found that most failures originate in the switch chamber. Water is the chief source of contamination. However, heavy contamination of askarel with petrolatum and asphalt material, due to leakage, have caused a few failures.

Petrolatum is used extensively for filling terminal chambers. When either cable oil or petrolatum seeps into askarel, no great harm results. The fire resistance will be somewhat decreased and power factor of the askarel will increase with an accompanying drop in resistivity. While highly undesirable, it is doubtful that failure of the unit results. Where asphaltic compounds are used, instead of petrolatum, the danger is increased. Sometimes, however, asphaltic contamination may cause excessively high dielectric losses in the askarel.

When the terminal chamber is below the switch chamber, the potting compound can be contaminated by askarel if the bushing seals are leaky. This is understood because the askarel will increase the power factor and conductivity of the potting compound or cable oil and develop heat from dielectric loss. If this mixture is drawn into the cable

TOWOLDMON0023626

[illegible] stable fluids similarly. This again emphasizes the importance of tight bushing assemblies.

III. Sealing Switches and Terminal Chambers

Proper bushing construction, use of Silastic seals and welding wherever possible is highly desirable (as covered in Section A). Where an elastomeric seal is to be used in contact with both askarel and petroleum oil, DuPont's Viton is suggested.

For new equipment the user should specify these modern sealing arrangements to keep out contaminants and minimize maintenance.

IV. Askarel Used Under Mild Arcing Conditions

The IEEE Guide for Transformer Askarel calls attention to the following:

"Askarel is used, to some extent, in apparatus where it is subjected to light intermittent arcing, such as in self-contained induction regulators, where operating switches are continually producing slight arcs. In transformer de-energizing switches, etc., (under normal conditions) deterioration of the askarel is very slight. However, improperly adjusted or defective switches in this type of apparatus can produce excessive and prolonged arcing and accelerated deterioration of the askarel. It is recommended that when askarel is used under these conditions, checks of the liquid, especially for moisture and dielectric breakdown voltage, made more frequently than when it is used only as a cooling and insulating fluid. Deterioration of this type is indicated by a blackening of the liquid. It can usually be reconditioned as previously described. Special attention should be given to maintaining the scavenger at the appropriate concentration."

V. Maintenance for Askarel Filled Switches

A. Switches used for grounding other power source has been de-energized will not [illegible] arcing.

B. Switches interrupting [illegible] current will be subject to arcing, the amount of decomposition will depend on power interrupted, time and [illegible] operation. As a general rule, the liquid should be checked after [illegible] operations.

1. On new [illegible] switches, check the askarel at 6 and 12 months following [illegible] factory check and [illegible] operation. Similar [illegible] to the gas [illegible] and gas [illegible] should probably indicate the [illegible] frequency of [illegible].

2. Check askarel for:

a. Dielectric breakdown voltage (ASTM D877). Should be 25 kV minimum [illegible] to breakdown voltage is low, confirm [illegible] by Karl Fischer method ASTM D 1533. Excessive moisture. Dielectric strength should not be [illegible] kV minimum.

b. Presence of carbon from arcing. Fluid should be relatively free of carbon. If badly arced and very black, replace fluid. If only minute amounts of carbon are present, filtration is recommended. Check power factor of liquid (should not be over 5% at 25°C and 60 cycles).

c. Flush out switch chamber with several gallons of fresh askarel before refilling.

3. If there is deterioration, high power factor, detectable change in specific gravity by refractive index, or if fluid flashes below 300°C, there is a possibility of the base of potting compound into the switch [illegible]. In this case, carefully [illegible] bushing seals with proper replacements and fill with new askarel.

4. If terminal chamber is below switch check, potting compound for [illegible] level can usually be detected by [illegible] in specific gravity. If askarel is present, correct [illegible] bushing seals with proper replacements, and renew compounds.

5. Gasketing cover gaskets visually. Deterioration can be detected

0145696

TOWOLDMON0023627

by swelling and cracking of the exposed edge. In cases of severe deterioration, liquid seepage is usually present.

3. Check for leakage at packing gland of switching shaft. If leaking, repack with a Silastic ring type gasket.


VI. Askarel Under Excessive Temperature or Fault Conditions

The IEEE Guide also points out that:

"Chlorobenzenes used in transformer askarels begin to boil at temperatures of about 205°C, under atmospheric conditions. If the material is heated to such high temperature in a sealed system, pressure develops. Pressure will also develop in the system if the askarel is arced sufficiently to generate copious hydrogen chloride gas.

"Therefore, it is recommended that wherever possible, sealed askarel-filled equipment be provided with pressure relief devices. These devices must be large enough to provide immediate relief at a definite pressure, and to prevent further build up of pressure if decomposition continues. It must be remembered that the presence of devices of this sort does not necessarily preclude the rupturing of containing vessels, since pressure build up can be extremely rapid under violent arcing conditions."

Section C
Toxicity & Safe Handling



I. Inhalation

At ordinary temperatures the chlorinated biphenyls in Askarel have not presented industrial toxicological problems. The hazard of potential toxic exposure varies with their volatility and lower chlorinated, more-volatile types present more of a potential problem from the standpoint of both inhalation and skin contact. When Askarel fluids are used at elevated temperatures, engineering controls must be applied, either by the use of closed systems or by effective local exhaust ventilation together with general workroom exhaust.

Vapors of Askarel at room temperature should not be breathed in a confined space, and the vapor of any fluid evolved at elevated temperatures should be allowed to be dispersed into the general workroom.

Inhalation tests on animals indicate that the maximum safe concentration of vapor is in the range of from 0.5 to 1.0 milligram per cubic meter of air. The threshold limit value (maximum allowable concentration of an 8-hour working day) set by the American Conference of Government Hygienists are 1.0 milligram of the lower-chlorinated biphenyl compounds per cubic meter of air and 0.5 milligram of the more-highly-chlorinated compounds, per cubic meter of air.

II. Skin Contact

Prolonged or repeated skin contact with the Askarel fluids must be avoided by the use of gloves and protective garments, because of the possible occurrence of a condition called chloracne. Although reports of this condition caused by Askarel are rare, it can be produced by excessive skin contact. If the fluid is spilled on the skin, the skin should be washed in the usual manner with a soap solution.

A burn caused by contact with a hot Askarel should be treated like any ordinary burn.

(For disposal instructions of Askarel fluids, see Section A - VIII, page 6.)

TOWOLDMON0023628

Section D Analytical Services on Transformer Askarel Available From Monsanto

Transformer users not wishing to make their own fluid analyses can obtain the service from Monsanto. Simply contact Monsanto and specify what analyses are wanted. You will be sent the proper-sized, clean sample container, fitted with a proper label. When you receive this, carefully take your sample (following the procedure for sampling in this guide). Send the container to Monsanto's laboratory. Charges listed include sample container and laboratory costs. The charges are those in effect March 1, 1976, and are subject to change.

Types of Analyses Available

Analysis 1)
ROUTINE MAINTENANCE CHECK — Total Charge: $30.00

To determine the general condition of the fluid and find whether further analysis is necessary. (one-quart sample required)

Properties Tested	Dielectric Breakdown Voltage
Color and Condition	Moisture

You will be notified of the results of this test. If further testing is indicated, and you want a complete analysis, you will be sent a five-pint sample container. This sample will be used for the following series of tests:

Analysis 2)
COMPLETE ANALYSIS — Total Charge: $75.00

(1) To determine the extent of fluid contamination, (2) earth refinement to determine what degree of restoration of electrical and insulating properties is possible, (3) check test to see how the fluid responded to earth treatment.

a) Complete Analysis: to determine the extent of contamination

Properties Tested	Free Chlorides
Color and Condition	Acidity
Specific Gravity	Dielectric Breakdown Voltage
Refractive Index	Power Factor, Dielectric Constant, and Resistivity
Water	

b) Earth Refinement Response:
Consists of treatment for 2.5 hours at 50-60°C. with 0.1 to 0.2 percent by weight of properly conditioned Attapulgus clay and then filtration through dry filter paper.

c) Analysis After Laboratory Earth Refinement:

Properties Tested	Acidity
Refractive Index	Dielectric Breakdown Voltage
Water	Power Factor, Dielectric Constant, and Resistivity
Free Chlorides	

You will be notified of the results of this test series on your sample. Then after refining your entire transformer fluid fill you can check on the results by requesting the following analysis:

Analysis 3)
ANALYSIS AFTER EARTH REFINEMENT — Total Charge: $50.00
(This charge will not apply when analyses 1 and 2 have already been made.)

To determine whether the entire lot of the askarel fill responded to the same extent as the laboratory sample. (five-pint sample required)

Properties Tested	Free Chlorides
Color and Condition	Acidity
Refractive Index	Dielectric Breakdown Voltage
Water	Power Factor, Dielectric Constant, and Resistivity

To arrange for the tests described above write to the following address:

David Wood
Monsanto Industrial Chemicals Company
800 North Lindbergh Blvd.
St. Louis, Missouri 63166

Samples to be tested should be clearly marked for identification and sent directly to:

Monsanto Company
W. G. Krummrich Laboratory
Sauget, Illinois 62201
Attention: R. Kuster

0145698

TOWOLDMON0023629

Section E Appendices

APPENDIX A

Askarel Stability and Composition of Arc Formed Gas: Askarel insulation is one of the most inert, chemically-stable heat resistant, non-corrosive liquids known. It will not break down, oxidize or sludge when exposed to air and high temperatures, 150°C. or even somewhat higher. Arcing, however, will break down the compound to liberate some hydrogen chloride and small amounts of carbon.

APPROXIMATE COMPOSITION
ARC-FORMED GAS FROM TRANSFORMER ASKAREL BLENDS
ASTM TYPES D AND G
(INERTEEN 70-30 AND PYRANOL A1338-3, RESPECTIVELY)

Gas	Amount
carbon monoxide	0.3%
carbon dioxide	0.3%
oxygen	0.6%
inert gases	1.5%
hydrogen chloride	97.3%
(note the absence of phosgene)	

This arc-formed gas from ASTM Type D and Type G transformer askarels is non-flammable and non-combustible.

For all practical purposes, the amount of gas liberated from askarel under a given set of arcing conditions is about 100 cubic centimeters per kilowatt second.

APPENDIX B

SOLUBILITY OF GAS IN TRANSFORMER ASKARELS
ASTM TYPES D AND G

	Percent of Gas By Volume Corrected to			
	25°C, 760 mm		0°C, 760 mm	
	25°C	100°C	25°C	100°C
Carbon [illegible]	21%	47%		
Air	8.7	4.8	5.8	5.0
Nitrogen	8.0	4.8	5.6	4.4
Hydrogen [illegible]	97.8	50.9		

In absorbing [illegible]

APPENDIX C

EFFECT OF TEMPERATURE ON DIELECTRIC BREAKDOWN VOLTAGE OF ASKAREL

Temperature °C	Dielectric Breakdown Voltage ASTM D877
[illegible]	67 KV
[illegible]	63
[illegible]	57
0	54
20	60
40	50
60	48
80	46

TOWOLDMON0023630

APPENDIX D

COMPARISON OF THE APPROXIMATE VISCOSITY IN SAYBOLT UNIVERSAL SECONDS OF TRANSFORMER ASKARELS AND MINERAL OIL

Temp. °C	Pyranol A1383B-3	10-C Mineral Oil	Inerteen 70-30
−20	1,000	1,000	2,600
0	100	150	195
20	70	85	85
40	45	49	50
60	39	40	40
80	34	34	36
100	30	30	33

APPENDIX E

THE DENSITY OF INERTEEN 70-30 AND TRANSFORMER PYRANOL A1383B-3

Approx. Density gm/cc.

Temp. °C	Inerteen 70-30	Pyranol A1383B-3
0	1.574	1.577
20	1.552	1.555
40	1.529	1.532
60	1.507	1.510
80	1.485	1.488

APPENDIX F

The thermal conductivity values of transformer Pyranol A1383B-3 at 27°C and 58°C are 26.2 and 25.8 x 10^{-5} calories centimeters^{-1}, degrees centigrade^{-1}, second^{-1}, respectively. Or, approximately 0.06 BTU per (hr.) (sq. ft.) (°F.) per foot. This same approximation applies to Inerteen 70-30.

APPENDIX G

Heat Capacity

Over the temperature range of 26° to 120°C the specific heat of transformer askarel is close to 0.30 calories per gram per degree.

APPENDIX H

Coefficient of Expansion

The average coefficient of expansion of transformer askarel over the temperature range 20 to 100°C is 0.0007 cc/cc/°C. One gallon would increase to 1.056 gallons on heating from 20 to 100°C.

APPENDIX I

Fire Resistance

Askarels of various compositional types are used. Under arcing conditions the gases produced, while consisting of predominantly non-combustible hydrogen chloride can yield varying amounts of combustible gases depending upon the askarel type.

Insulation systems incorporating these askarels and cellulosic or other organic materials may, when arced, produce gaseous mixtures which are moderately flammable. As a precaution, such gases should be removed from the askarel by bubbling dry nitrogen through the askarel and purging the tank space with dry nitrogen before any work is performed on the apparatus.

TOWOLDMON0023631

APPENDIX J

Seals, Properties and Procurement

Dow Corning Corporation, Midland, Michigan with Districts at Atlanta, Boston, Chicago, Cleveland, Dallas, Los Angeles, New York City, Washington, D.C. and Toronto has available Bulletin 09-019, August 1962 entitled "Silastic Design Data". This lists the gasket fabricators throughout the country from whom the "Silastic 50" gasketing can be purchased in sheet, extrusions or molded shapes.

Generally, Silastic 50 sheet goods are stocked by local die cutters, hence, could be generally purchased locally. Usually small quantities of gaskets are die cut. If larger quantities are needed, tools are made of the same type used to cut other elastomers.

Where the gasket is extruded for fitting into a machined groove or between gasket stops, Dow Corning advises use of a scarved joint. This joint is then cemented using Dow Corning's Silastic 140 (clear) or their RTV 731 (white) materials, which air cure.

Dow Corning points out that the local "rubber" fabricators purchase the Silastic 50 in billet form. This is worked on a roll mill in preparation for sheeting or extrusion. Then to obtain the desired physical properties the fabricator must oven cure the Silastic 50 for 24 hours at 480°F.

SPECIFICATIONS*

	Color	White
	Specific Gravity at 77°F	1.20 ± 0.02
ASTM D676	Hardness, Shore A. Scale	45 to 60
ASTM D412	Tensile Strength, psi, min	800
ASTM D412	Elongation, percent, min	250
ASTM D395	Compression Set after 22 hrs at 300°F, percent, max	30

*All physical properties measured on 0.075 inch thick samples molded 5 minutes at 240°F, and oven cured 24 hours at 480°F.

APPENDIX K

Caution Label

The following or equivalent caution statements should be fixed on all containers of transformer askarels and the transformers themselves:

This product contains Polychlorinated Biphenyls (PCBs). Care should be taken to prevent entry into the environment through spills, leakage, use, vaporization, or disposal of liquid or containers. Avoid prolonged breathing of vapors or mists. Avoid contact with eyes or prolonged contact with skin. If skin contact occurs, remove by washing with soap and water. Following eye contact, flush with water. In case of spillage onto clothing, the clothing should be removed as soon as practical, skin washed, and clothing laundered.

Monsanto

MONSANTO INDUSTRIAL CHEMICALS COMPANY
SPECIALTY PRODUCTS GROUP
800 N. LINDBERGH BLVD.
ST. LOUIS, MISSOURI 63166

The information herein regarding obtaining optimum results from askarel fluids in your transformer has been accumulated by Monsanto for over 40 years from the experience of makers and users of askarel transformers and it is believed will be helpful.

Nothing herein shall be construed as applying to other than askarel insulation. Data and maintenance suggestions herein do not apply to the other components of the transformer. All operating and maintenance suggestions recommended by the manufacturer of the transformer should also be carefully followed.

Because these maintenance directions apply only to the askarel insulation, Monsanto disclaims any liability for damage to property or injury to persons arising from transformer operation.

0145701

TOWOLDMON0023632

U S CUSTOMER SERVICE CENTERS

AKRON, OHIO 44313
388 Springside Drive
Montrose Development Park
Tel. (216) 666-4111

ATLANTA, GEORGIA 30339
339 Interstate North Parkway
Suite 600
Tel. (404) 434-4949

BOSTON, MASSACHUSETTS 02149
Everett Station
Tel. (617) 387-5010

HOUSTON, TEXAS 77027
1301 Post Oak Tower
5051 Westheimer Road
Tel. (713) 621-9550

LOS ANGELES, CALIFORNIA
1401 Dove Street
Newport Beach, California 92660
Tel. (714) 833-9150

NEW YORK, NEW YORK 10036
11114 Avenue of the Americas
Tel. (212) 764-5000

ST. LOUIS, MISSOURI 63166
800 N. Lindbergh Blvd.
Tel. (314) 694-1000

SAN FRANCISCO BAY AREA
2710 Lafayette
Santa Clara, California 95052
Tel. (408) 243-0414

WILMINGTON, DELAWARE 19810
Suite 204, Bancroft Bldg.
3411 Silverside Road
Tel. (302) 478-4800

INTERNATIONAL OFFICES

ARGENTINA
Monsanto Argentina S.A.I.C.
Avda Madero 1020, Floors 17th & 18th
Buenos Aires, Argentina

AUSTRALIA
Monsanto Australia Limited
East Tower, Princes Gate Bldg.
181 Flinders Street
Melbourne, Victoria 3001
Australia

Monsanto Australia Limited
35 Terry Street
Rozelle, Sydney, NSW
Australia 2039

Monsanto Australia Limited
Post Office Box 1111K, Adelaide
South Australia 5001

Monsanto Australia Limited
Brisbane
P. O. Box 63, Hamilton Central
Queensland, Australia 4007

Monsanto Australia Limited
Perth
P. O. Box 77
Doubleview
West Australia 6018

AUSTRIA
Monsanto GmbH Austria
Rudolfsplatz 12
A-1010 Wien 1, Austria

BELGIUM
Monsanto Europe S.A.
1, Place Madou
1030 Brussels, Belgium

Monsanto Europe NV/SA
163 Mechelsesteenweg
2000 Antwerp, Belgium

BRAZIL
Industrias Monsanto Ltda.
Rua Arouje 216, 6 Andar
Sao Paulo, Brazil 01220

CANADA
Monsanto Canada Ltd.
178 Rexdale Blvd.
Rexdale, Ontario, Canada

Monsanto Canada Ltd.
100 Park Royale, Suite 701
West Vancouver, B.C., Canada

CHILE
Monsanto Chile Comercial e Industrial
Limitada
Edificio Espana Oficina 502
Calle Estado 337
Santiago de Chile

COLOMBIA
Monsanto Colombiana Inc.
Carrera 14, No 77 - 59
Bogota, Colombia

DENMARK
Monsanto A/S
6 Ryvangsvangsgade
DK 1564 Copenhagen
Denmark

EL SALVADOR
Monsanto Centroamerica (El Salvador) S.A.
Edificio Plaza
67 Avenida Sur y Calle a Santa Tecla
San Salvador, El Salvador

FINLAND
Monsanto (Scandinavia) AB
Arkadiankatu 8 C 20
00100 Helsinki 10, Finland

FRANCE
Societe Monsanto S.A.
9 rue d'Argenson
75 Paris (8) France

GUATEMALA
Monsanto Guatemala Inc.
Edificio Cata
7a Avenida 7-11 Zona 9
Guatemala City, Guatemala

HONG KONG
Monsanto Far East Ltd.
Management House, 2nd Floor
26 Canal Road West
Hong Kong, B.C.C.

INDIA
Mindia Chemicals Ltd.
Monsanto Chemical of India Pvt. Ltd.
(Ag Products)
Wakefield House
11 Sprott Rd., Ballard Estate
Bombay 400 001, India

Mindia Chemicals Ltd.
19 Rajendranath Mukherjee Rd.
Calcutta 700 001, India

Mindia Chemicals Ltd.
Monsanto Chemicals of India. Pvt. Ltd.
(Ag Products)
310-311 Linghi Chetty Street
Madras 600 001, India

Mindia Chemicals Ltd.
3/8 Asef Ali Road
New Delhi 110 001, India

INDONESIA
P. T. Monsanto Pan Electronics
191 Dj. Dr Sahardjo
Jakarta, Indonesia

ITALY
Monsanto Italiana S.p.A.
Via Maldehiarro Gioia 6
Milano 20124, Italy

JAPAN
Monsanto Japan Ltd.
Room 217, Shin Kokusai Bldg.,
4-1, Marunouchi 3-chome
Chiyoda-ku, Tokyo, Japan

MALAYSIA
Monsanto Far East Ltd.
(Malaysia Branch)
116, Jalan Semangat
Petaling Jaya, Selangor, Malaysia

MEXICO
Monsanto Comercial S.A. de C.V
Thiers No. 249
Mexico 6, D.F., Mexico

NETHERLANDS
Monsanto B.V.
Jan van Nassaustraat 53-55
Den Haag
The Netherlands, Holland

NEW ZEALAND
Monsanto New Zealand Ltd.
18 Green South Road
Remuera
Auckland 5, New Zealand

NICARAGUA
Monsanto (Nicaragua) S.A.
P. O. Box 288
Managua, Nicaragua

NORWAY
Monsanto Norge A.S.
Fred Olsensgate 11
Oslo 1, Norway

PHILIPPINES
Monsanto Philippines Inc.
Suite 1101 Security Bank & Trust
6788 Ayala Ave.
Makati Rizal D-708, Philippines

PUERTO RICO
Monsanto Puerto Rico Company
Munoz Rivera Ave. Borriquen St.
Rio Piedras, Puerto Rico

SINGAPORE
Monsanto Singapore Company (Pte.) Ltd.
Suite 706 Cathay Bldg., 7th Floor
Mount Sophia, Singapore 9

SOUTH AFRICA
Monsanto South Africa (Pty.) Ltd.
11th Floor, Sandton City Bldg.
Sandton, Transvaal, South Africa

SPAIN
Monsanto Iberica S.A.
Lepanto 350-6
Barcelona 13, Spain

SWEDEN
Monsanto (Scandinavia) AB
Ulvsundavegen 108
Bromma, Sweden

SWITZERLAND
Monsanto (Suisse) S.A.
Tiefenhofe 10,
CH8022 Zurich, Switzerland

TAIWAN
Monsanto Far East Ltd. - (Taiwan Branch)
38 Cheng An East Road, 6th Floor
Section 1, Taipei
Taiwan

THAILAND
Monsanto Thailand Ltd.
6th Floor, Kasemkij Bldg.
120 Silom Road
Bangkok, Thailand

UNITED KINGDOM
Monsanto Ltd.
10-18 Victoria Street
Monsanto House
London SW1H ONQ England

VENEZUELA
Monsanto (Venezuela) CA
Torre Phelps Piso 24
Plaza Venezuela
Caracas 101, Venezuela

WEST GERMANY
Monsanto (Deutschland) GmbH
Immermannstrasse 3
D-4000 Duesseldorf, West Germany

Monsanto

Monsanto Industrial Chemicals Co. / A Unit of Monsanto Company / 800 N. Lindbergh Blvd., St. Louis, Mo. 63166

2-3642-0475-6

0145702

TOWOLDMON0023633