


TRANSFORMER

Askarel

Inspection & Maintenance Guide

Monsanto



0249287

TOWOLDMON0027872

WATER_PCB-00012341

Table of Contents

SECTION A	
TRANSFORMER ASKARELS	1
I. Introduction	1
II. History of Trade Name Types	1
Table I - The Composition of Transformer Askarels	2
III. Interchangeability	2
IV. Table II - Official Transformer Askarel Shipping Specifications	3
V. Ordering Instructions	3
VI. Stability	3
VII. Precautions When Handling Drums, Tank Cars and When Opening Transformers	4
A. Keep Dry During Handling	4
Table III - Handling and Pumping Temperatures	4
B. Use Ordinary Personal Precautions	4
C. Precautions on Opening an Askarel Transformer	5
VIII. Avoid Environmental Pollution	5
1. Labeling Askarel Transformers	5
2. Disposal of Liquid and Solid Wastes	5
3. Conditioning of New or Recycled Askarel	6
4. Teardown of Transformers for Repair or Scrap	7
5. Transformer Disposal	7
IX. Expected Service Life	7
X. General Characteristics of Transformer Askarel Fluid	7
XI. Sampling Transformer Askarel Fluid	8
XII. Evaluation of Askarel Recycled in New Equipment	8
XIII. Dielectric Breakdown Voltage Moisture Relationship	9
Table IV - Relation of Dielectric Breakdown Voltage to Amount of Dissolved Water in Askarel and Mineral Oil	9
Table V - Approximate Solubility of Water in Transformer Askarel and Mineral Oil	10
XIV. Turbidity	10
XV. Check Points for Maintaining Askarel Insulation	10
A. General Considerations	10
B. Modern Sealing Procedures	11
C. The Older Sealing Arrangements	12
XVI. Periodic Fluid Inspection and What Checkpoints Mean	12

A. Visual Inspection	13
B. Dielectric Breakdown Voltage	13
XVII. Inspection Checklist	13
XVIII. Contamination in Transformers	14
Table VI - Effect of Common Insulation Materials on Power Factor and Dielectric Strength	14
Table VII - Effect of Common Insulation Materials on Volume Resistivity of Askarel	14
XIX. ASTM Method for Investigating the Compatibility of Transformer Insulation and Construction Materials in Askarels	15
XX. Refining Askarel for Re-Use	16
A. Filtering Through Dry Blotter Paper to Remove Moisture and Extraneous Particles	16
Table VIII - Water Removal by Filtering Askarel Through a Paper Press	16
B. Disposal of Solid Wastes	16
C. Solid Insulation Requiring Drying	16
D. Earth Treatment for Maximum Improvement of Power Factor and Volume Resistivity	16
Table IX - Effect of Power Factor and Volume Resistivity	17
XXI. Cleaning Arced Transformers	17
XXII. Sampling Askarel	17

SECTION B	
ASKAREL FILLED SWITCHES AND TERMINAL CHAMBERS	19
I. Introduction	19
II. Sources of Contamination	19
III. Sealing Switches and Terminal Chambers	20
IV. Askarel Used Under Mild Arcing Conditions	20
V. Maintenance for Askarel Filled Switches	20
VI. Askarel Under Excessive Temperature or Fault Conditions	21

SECTION C	
ANALYTICAL SERVICES ON TRANSFORMER ASKAREL AVAILABLE FROM MONSANTO	22
Types of Analyses Available:	22
1) Routine Maintenance Check	22
2) Complete Analysis	22
3) Analysis After Earth Refinement	22
Appendix A - Askarel Stability and Composition of Arc Formed Gas	23
Appendix B - Solubility of Gas in Transformer Askarels	23
Appendix C - Effect of Temperature on Dielectric Breakdown Voltage of Askarel	23
Appendix D - Comparison of the Approximate Viscosity in Saybolt Universal Seconds of Transformer Askarels and Mineral Oil	24
Appendix E - The Density of Inertben 54201 KA 7336-9 and Transformer Pyranol A138B-3	24
Appendix F - Thermal Conductivity Values of Transformer Pyranol A138B-3	24
Appendix G - Heat Capacity	24
Appendix H - Coefficient of Expansion	24
Appendix I - Fire Resistance	24
Appendix J - Seals, Properties and Procurement	25
Appendix K - Caution Label	25

SECTION D
TOXICITY & HANDLING
APPENDICES

Pyranol

0249288

Section A Transformer Askarel

as manufactured
by Monsanto

fire-resistant*

I. Introduction

The term "askarel" as defined by IEEE, ASTM and the National Electrical Code generally describes a broad class of non-flammable synthetic chlorinated hydrocarbon insulating liquids widely used in transformers, reactors and accessory equipment operated at power frequencies. Askarels of various compositional types are in use. (For the general properties and types see ASTM D-2283.) Under arcing conditions the gases produced, while consisting of predominantly non-combustible hydrogen chloride, can contain varying amounts of combustible gases depending upon the askarel type.

This manual describes the operating characteristics of transformer askarel liquid insulation and how it differs from mineral oil. Appropriate handling and disposal procedures for both scrap askarel liquid and impregnated solid materials are given in accordance with the guidelines recommended by the American National Standards Institute.

The information is based on facts gathered by Monsanto over 40 years as a producer of askarel, plus knowledge gained from the experience of transformer manufacturers and users. This guide outlines the very simple maintenance required for askarel fluid in "modern" transformers and offers suggestions for sealing and maintaining askarel in old units. By following this guide, we believe users will obtain maximum service from askarel insulation with a reasonable minimum of maintenance. If questions arise relating to the designing and building of transformers, these should be referred to regular transformer suppliers.

Monsanto gratefully acknowledges the assistance, guidance and the contributions of certain data by the following:

Edward L. Raab -- General Electric
Dr. T. K. Skoat -- Westinghouse Electric

II. History of Trade Name Types

"Askarel" is the generic name for the non-combustible liquid insulation and coolant first used by General Electric Company in 1932 for their Pyronel® brand name fire-resistant transformers. Westinghouse Electric Corporation uses their brand name, Inerteen®.

Whatever the trademarked brand, the askarel contains chlorinated biphenyl -- one of the best liquid insulations developed by science. This inert material is chemically stable, fire-resistant, heat stable, non-corrosive, and has high dielectric strength under the operating conditions encountered in transformers.

In addition to manufacturing Aroclor® (chlorinated biphenyl), Monsanto also mixes this dielectric fluid with chlorobenzenes to produce the presently used Inerteen and Pyronel blends described in Table I.

- * Trademark of General Electric Company
- ** Trademark of Westinghouse Electric Corporation
- ® Registered trademark of Monsanto Company

0249289

Table I
The Composition of Transformer Askarel

Method ASTM D 2283

Type D	Type E	Type G
Inertion 70-30	Inertion 100-0	Pyranol A1383B3

Ingredients (W by Wt)

Arcofire 1264, pentachlorophenyl	70	0	0
Arcofire 1247, trichlorophenyl	0	100	0
Arcofire 1247, trichlorobenzene	0	0	40
Arcofire 1247, tetrachlorobenzene	0	0	0
Phenoxypolyene oxide scavenger	0.18 to 0.22	0.18 to 0.22	0.115 to 0.130
Peroxide scavenger			
Method ASTM D 2283 pending			

ASTM Method D 2283, titled "Chlorinated Aromatic Hydrocarbons (Askarel) For Transformers", also lists the composition of all transformer askarels used at various times since 1932.

Montanto manufactures similar transformer askarel fluids in England where the trade name Pyroclor is used.

III. Interchangeability

In general all transformer askarels are interchangeable. However, it is suggested that the transformer manufacturer be consulted prior to mixing in significant proportions or total substitution.

IV. Official Transformer Askarel Shipping Specifications

The official shipping specifications for the three modern transformer askarel fluids are shown in Table II.

V. Ordering Instructions

Montanto's current policy is to sell askarel transformer fluids only to transformer manufacturers. Others interested in these fluids should contact the manufacturers of askarel transformers and not Montanto. The transformer name plate indicates the transformer maker and usually gives sufficient data to identify the specific askarel fluid used.

VI. Stability Contamination

Askarel liquid insulation is highly pure, fire resistant liquid made under close chemical control to meet the existing specifications as shown in Table II. It does not vary in composition like the commercial range of mineral oils.

Askarel insulation must never be mixed with mineral oil. Over two percent of mineral oil by volume in askarel begins to lower its fire resistance.

Askarel does not deteriorate when exposed to air, hot, hot metal, it does not break down over long use to form conducting or corrosive chemicals. It does not oxidize or sludge. Askarel will remain perfectly stable year after year unless broken down by severe electrical discharge.

In modern transformers, the only real enemy of askarel is contamination by water. Keeping askarel water-free will insure long life service.

Askarel is heavier than water. If water gets into askarel insulation, only

*Chlorinated Biphenyl
(54% Chlorine by weight)*

*Chlorinated Biphenyl
(42% Chlorine by weight)*

0249290

Table 11

Official Transformer Askarel Shipping Specifications

Specification Properties	General Electric Co. Transformer Pyranol A13838-3 ASTM D2283 Type G*	Westinghouse Transformer Inertan 70-30 ** ASTM D2283 Type D	Westinghouse Transformer Inertan 100-42 ** ASTM D2283 Type E
Color, APHA	150 max.	150 max.	50 max.
Condition	Clear	Clear	Clear
Water content, ppm (ASTM D1533-60)	30 max.	30 max.	35 max.
Acidity, mg KOH/g (ASTM D974-55)	0.014 max.	0.014 max.	0.01 max.
Dielectric strength, 25°C, 0.1 in. gap (ASTM D877-49)	35 KV min.	35 KV min.	35 KV min.
Dielectric Constant, 100°C, 60 Hz (ASTM D924-49)	4.2 to 4.6	4.2 to 4.5	4.7 to 4.8
Volume Resistivity, 100°C, 500 volts DC 0.1 inch gap, 10 ⁹ ohm-cm (ASTM D1189)	100	100	100
Inorganic chlorides, ppm (ASTM D1821 and G.E. Method E4C418)	0.10 max.	0.10 max.	0.05 max.
Refractive index, 25°C (ASTM D1807)	1.6110 to 1.6120	1.6153 to 1.6173	1.6240 to 1.6260
Viscosity at 37.8°C (ASTM D88-58)	44 to 48	56 to 61	82 to 92
Saybolt Universal Seconds			
Pour Point °C (ASTM D-97-57)	38 or lower	30 or lower	17 or lower
Specific gravity 25/15.5°C (ASTM D1810)	1.485 to 1.510	1.518 to 1.528	1.381 to 1.392
Burn point (ASTM D92)	None to boiling	None to boiling	None to boiling
Distillation range (ASTM D20-56) corrected for stem and barometric pressure	1st drop 200°C min. 40% max. below 270°C 90% 379 to 394	1st drop 200°C min. 35% below 270°C 90% 379 to 394	10% 325°C min. 90% 360 max.
Fixed chlorine	55.4 ± 0.5%	55.6% min.	43 ± 0.5%
Corrosion test	After heating with aluminum for 6 hrs. at 200 to 220°C, the aluminum must not be corroded on either visual or weight inspection and the askarel should meet the following specifications:		
Color, APHA	200 max.	200 max.	200 max.
Acidity, mg KOH/g	0.014 max.	0.014 max.	0.01 max.
Inorganic chlorides ppm	0.15 max.	2.0 max.	0.15 max.
Condition	Clear	Clear	Clear
Solvent content	0.115 to 0.135% Dioxoxide	0.18 to 0.22% phenoxypiprene oxide	0.18 to 0.22% phenoxypiprene oxide
Typical Properties			
Coefficient of Thermal Expansion (ASTM D1903), cm ³ /cm ³ /°C	0.0007	0.0007	0.00068
Arc formed gases	Askarels of various compositional types are used. Under arcing conditions the gases produced, while consisting predominantly of non-combustible hydrogen chloride, can include varying amounts of combustible gases depending upon the askarel type. Insulation systems incorporating these askarels and cellulosic or other organic materials may, when arced, produce gaseous mixtures which are moderately flammable. As a precaution, such gases should be removed from the askarel by bubbling dry nitrogen through the askarel and flushing the gas space with dry nitrogen before any work is performed on the apparatus.		

*Method ASTM D2283 pending for Type G.

**Westinghouse uses their private number Inertan 54201KA for Inertan 70-30 and their private number Inertan 54201CM for Inertan 100-42.

Pick up disclaimers

a tiny amount (approximately 126 ppm) dissolves in the rest floats on top. Askarel is very insoluble in water, only about 200 parts per billion of askarel dissolve in water, at normal temperatures.

VII. Precautions When Handling Drums, Tank Cars, and When Operating Transformers

The American Institute of Electrical and Electronic Engineers Guide No. 76, December, 1958 has been revised to give more detailed instructions and guidance "For Acceptance and Maintenance of Transformers Askaled in Equipment". This guide is published by the Institute of Electrical & Electronics Engineers, Inc., 345 East 47th Street, New York, New York 10017.

The following are significant precautions:

A. Keep Dry During Handling:

In handling, storing, sampling and inspecting askarel -- and in operating askarel transformers -- take every precaution to guard the askarel insulation from exposure to high humidity and moisture contamination. Keep 6 or 65 gallon drums of askarel dry; lay stored drums on their sides with the bung at the highest point from floor to keep water off the drum head (which can be sucked into the askarel by the drum "breathing"). This precaution is not necessary when drums are stored indoors, which is the preferred place for storage.

To avoid leakage the drums used for askarel are of heavy construction. Sixteen gauge metal is used, with special rim seal and bung construction. The drums should be drained as completely as possible and then flushed twice with kerosene type solvent to remove all of the askarel. Accumulated liquids and washings should be collected and should be incinerated at high temperatures, e.g., about 2000°F, to destroy the polychlorinated biphenyls (PCBs). See Section A, VIII.

Tank cars used to transport askarels are in exclusive service and not used interchangeably for other products. All cars must be unloaded through the top (dome fitting) either by pumping or with controlled pressure using dry air or dry nitrogen. If nitrogen has been used for unloading it is necessary to advise the shipper so that when the car returns the nitrogen can be replaced with dry air before any one may enter the car. If the car is to be unloaded by pumping it will be necessary to use a dryer on the air intake line to remove moisture.

All tank cars are fitted with steam coils, which are available for unloading under extreme low temperature conditions.

Convenient handling and pumping temperatures and the related approximate viscosity ranges are given in Table III.

B. Use Ordinary Personal Precautions:

Transformer askarel has been made, handled, and used for over 40 years. It can be handled safely with recommended precautions. If accidentally spilled on hands, no serious skin irritation will occur. However, liquid askarel has a solvent action (similar to paint).

Table III
Handling and Pumping Temperatures

Product	Unloading, Handling and Pumping Temperature °C	Approximate Viscosity SUS
Pyranol A1383B-3	20-55	100-40
Inerteen 70-30	20-65	100-40
Inerteen 100-42	35-75	100-40

0249292

TOWOLDMON0027877

WATER_PCB-00012346

thinner) on the fats and oils of the skin and prolonged contact may lead to drying and chapping of the skin.

In case of contact with the skin with soap and water, remove and dry clean saturated clothing. Clean up spills with rag, sawdust and absorbent clay. Eye contact may result in painful irritation but no permanent damage to tissues. If askarel gets in the eyes, flush with large amounts of water. As with all eye first aid, refer to a physician. To relieve irritation, physicians have used an ophthalmic anesthetic solution as well as ophthalmic cortisone acetate solution, or castor oil.

Infrequent exposure to askarel vapors will not cause ill effects. However, prolonged exposure to high vapor concentrations should be avoided. If hot askarel must be handled in a closed or confined area, provide the area with mechanical exhaust ventilation - or wear an organic cartridge respirator approved by the U.S. Bureau of Mines.

C. Precautions On Opening an Askarel Transformer:

Askarels of various compositional types are used. Under arcing conditions the gases produced, while consisting of predominantly non-combustible hydrogen chloride, can yield varying amounts of combustible gases depending upon the askarel type.

Insulation systems incorporating these askarels and cellulosic or other organic materials may, when arced, produce gaseous mixtures which are moderately flammable. As a precaution, such gases should be removed from the askarel by bubbling dry nitrogen through the askarel and flushing the gas space with dry nitrogen before any work is performed on the apparatus.

VIII. Avoid Environmental Pollution

Transformer askarels contain polychlorinated biphenyls (PCBs) which have been used in the United States and elsewhere over the past 40 years for many industrial and consumer applications. During the past several years evidence has accumulated to indicate that PCBs are widely dispersed throughout the environment and that they can have adverse ecological and toxicological effects.

The United States Government's Interdepartmental Task Force on PCBs, Com-72-10418, in their March 20, 1972 report titled, "Polychlorinated Biphenyls and the Environment", recommended restricting PCBs to use in capacitors and transformers.

This report is distributed by the National Technical Information Service, U.S. Department of Commerce, Springfield, Virginia 22151.

A document titled, "Guidelines for Handling and Disposal of Capacitor and Transformer Grade Askarels, Containing Polychlorinated Biphenyls", has been prepared and is available from the American National Standards Institute, Committee C107, 155 East 44th Street, New York, New York 10017.

The scope, objectives and the composition of this committee are:

ANSI Committee C107

Scope:

Procedures and guides for safe use, maintenance and disposal of askarel and askarel-soaked materials used in electrical equipment.

Objectives:

1. Supply of technical information and advice for Federal, State, local authorities and all others concerned.
2. Encourage development of suitable disposal facilities and keep all concerned informed.
3. Serve as the advisory group for United States participation in international organizations: CEE, IEC, CIGRE.

0249293

5

TOWOLDMON0027878

WATER_PCB-00012347

Composition:

Organizations active in or represented by this ANSI Committee include: National Electrical Manufacturers Association, Electronic Industries Association, Institute of Electrical and Electronic Engineers, American Society for Testing and Materials, Electric Light and Power Association, Certified Ballast Manufacturers Association, Environmental Protection Agency, Office of Environmental Affairs, General Services Administration, National Bureau of Standards, Department of the Army, Rural Electrification Administration, Division of Environmental Research, TVA, American Public Power Association, Water Pollution Control Federation, Food and Drug Administration, National Fire Protection Association, Underwriters Laboratories, and several sections of the U.S. Department of Interior.

The following are pertinent excerpts taken from the ANSI Guidelines for askarel transformers:

1. LABELING ASKAREL TRANSFORMERS

"All new askarel transformers should be labeled:

Caution

The Insulating Liquid In This Transformer Contains Polychlorinated Biphenyls (PCBs). Care Should Be Taken To Prevent Entry Into The Environment In Case Of Malfunction Or Leaks. Consult The Instruction Manual Or The Manufacturer.

The transformer manufacturer should make similar warning labels available for use on previously installed transformers."

2. DISPOSAL OF LIQUID AND SOLID WASTES


"Disposal of askarel fluid and askarel-soaked materials must be accomplished by means in which there is no significant release of askarel to the environment. At present, disposal is accomplished by carefully controlled high temperature incineration of liquids and soaked software, and by controlled dry land-fill burial of apparatus and other hardware from which askarel has been previously drained and washed.

"Present knowledge indicates that proper incineration should involve a suitable balance between dwell time and temperature in the incinerator plus oxygen availability and finally suitable scrubbers to remove HCl formed, e.g. (1) two-second dwell time at approximately 2000°F and 3% excess oxygen in stack gas; (2) 1-1½ second dwell time at 2700°F and 2% excess oxygen in stack gas."

The ANSI Guide lists the locations of facilities that conform with the above requirements. Monsanto has such an incinerator at the W. G. Krummrich Plant, Department A-248, Saug L, Illinois 62201, where arrangements can be made for scrap askarel liquid disposal for a modest fee, currently 3 cents per pound. For disposal of solid scrap a controlled dry land-fill can be used where permitted by Federal, State and local regulations.

3. CONDITIONING OF NEW OR RECYCLED ASKAREL

Conditioning of new askarel or recycled askarel requires Fuller's earth treatment. The spent Fuller's earth in cartridges or bags when replaced should be allowed to thoroughly drain over drip pans to remove as much liquid askarel as possible. The cartridge unit of steel mesh construction should be placed in the "Steel Contaminated with Askarel" container for disposition. Cloth bags filled with Fuller's earth should be placed in the "Scrap Burnable Askarel Waste" container for disposition.



4. TEARDOWN OF TRANSFORMERS FOR REPAIR OR SCRAP

- Drain all askarel from the unit either into a holding tank for reuse or into the drum labeled "Scrap Askarel" for disposition, then allow sufficient time for all the askarel to drain from the core and coils.
- Remove the core and coil assembly from the transformer and place it on the floor. Sufficient absorbent material should be placed on the floor to absorb any askarel fluid that still drips from the transformer.
- Place all materials in the appropriate salvage containers during the dismantling for later disposition.
- All used materials, including rags, sawdust, talco, etc., regardless of quantity, should be put into the appropriate containers for disposition.

5. TRANSFORMER DISPOSAL

The ultimate disposal of an askarel-filled transformer may be accomplished in either of two ways:

- Complete draining and dismantling with the proper disposal of the askarel liquid and askarel-soaked components as described above.
- Disposition of askarel transformers by means of junk or scrap dealers should be avoided unless a transformer is first drained, followed by soaking of the interior with a suitable solvent, such as kerosene. Accumulated liquids and washings are to be disposed of as described earlier.

IX. Expected Service Life

Manufacturers indicate that properly designed and installed askarel transformers are expected to give trouble-free service for at least 30 years. Since their introduction in 1932, the manufacturers report finding the overall failure rate to be less than 0.5% for all units under test and service conditions. The Edison Electric Institute's report (1950-1958) on their member utilities, publishes the failure rate for askarel transformers as 0.13 per hundred banks per year.

Mr. Frank M. Clark, who invented transformer askarels at the General Electric Company in the early 1930s, made the highly pertinent comment based on his many years of experience with G.E. Pyrexol (askarel type) transformers that -

"The important thing is to keep them dry - otherwise leave them alone."

These words of wisdom became especially applicable in more recent years when welding shut rather than gasketing became the main method of sealing askarel transformers. These units are sold with the understanding that the liquid is in a normally hermetically closed system.

X. General Characteristics of Transformer Askarel Fluid

Appreciation of the following characteristics, as given in the IEEE Guide, leads to understanding the reasons for selecting dielectric breakdown voltage and moisture as the prime practical tests to judge the quality of transformer askarel fluid. Also, due to these characteristics the power factor of transformer askarel will be normally much higher than the corresponding values for mineral oil.

In comparison to mineral insulating oil, askarel is a relatively polar material, i.e., its molecules are dipoles, free to rotate around their axes and responsive to orientation by electrical forces. Askarel also exhibits a much higher dielectric constant and capacitance than insulating oil, and these differences must be kept in mind when interpreting electrical test data.

Because it is relatively polar and possesses high solvency power, askarel is much more effective than mineral oil in dissolving traces of extraneous soluble polar materials, and consequently the choice of

0249295

Construction materials destined for use in a.c. is very critical. This sensitivity is reflected in the power factor and moisture (specific resistance) of the askarel.

It is important to note that, with the exception of water, the dielectric breakdown voltage of askarel is not generally adversely affected by many of the soluble polar materials to which its power factor and its ohmic specific resistance are so sensitive. In fact, the dielectric breakdown voltage of askarel is somewhat greater than that of insulating oil. Therefore, the values assigned these dielectric fluids in newly supplied transformers are 30 KV min. and 26 KV min. respectively.

As with insulating oil, askarel must be kept dry. It can pick up moisture from exposure to humid atmosphere. Under similar conditions of exposure, askarel can pick up nearly twice as much moisture when measured on a parts per million weight basis.

XI. Sampling Transformer Askarel Fluid

The following precautions about sampling are quoted from the IEEE Guide:

"Representative samples, whether of the complete contents or only parts thereof, are extremely important from the standpoint of evaluation of the quality of the product sampled. Obviously careless sampling procedure or contamination in the sampling equipment will result in a sample that is not truly representative. This generally leads to erroneous conclusions concerning quality and incurs loss of time, effort, and expense involved in securing, transporting, and testing the sample. It is strongly recommended that all of the procedures and precautions outlined in the latest revision of ASTM D 923 (Sampling Electrical Insulating Liquids) be followed.

"Because of the high specific gravity (relative density) of askarel (greater than 1), water and some other impurities are most likely to be found at or near the surface. The top sample, therefore, is considered to represent the worst condition."

XII. Evaluation of Askarel Received in New Equipment


Some users of askarel equipment find it desirable to make "as received tests" on all equipment. It is quite common to use the dielectric breakdown voltage test and visual appearance as the most significant tests. If suitable equipment and trained personnel are available additional information may be obtained from the power factor, color, and moisture content tests.

In sampling askarel contained in apparatus extreme care must be exercised in order to obtain a representative sample. ASTM Method D 923 should be followed.

New equipment with askarel exhibiting the following characteristics is considered acceptable:

		ASTM Methods
Dielectric Breakdown Voltage	30 KV min.	D 877
Color	300 max. (Shrew color)	D 2129
Condition, Visual	Clear	D 1702
Water Content	25 ppm max.	D 1533
Power Factor at 25°C		D 924, D 1530

The power factor of askarel taken from new transformers, reactors and generator equipment can reflect the presence of moisture, dissolved polar compounds, or other contaminants and may vary with the type of equipment from which the sample was taken due to the different ratios of liquid to solid insulation and to the conductivity power of the askarel. Given any acceptable water content and dielectric breakdown voltage of the askarel as indicated above, a high power factor seldom impairs the serviceability of the askarel within either broad limits and is



indicator of the degree of extraneous soluble polar materials present.

Recognizing the possibility of a wide range of power factors being required for use in new equipment, it is difficult to establish a single limit which would be acceptable to both suppliers and users for all applications. However, as a rough guide, power factors up to about 10% at 25 and 60 cycles per second (hertz) do not in general indicate any abnormal contamination providing that the other factors (water content, dielectric breakdown voltage, etc.) are met. Much higher power factors may indicate excessive contamination or the misapplication of the solid materials used in manufacture in contact with the askael and should be investigated.

XIII. Dielectric Breakdown Voltage - Moisture Relationship

The dielectric breakdown voltage of askael is highly sensitive to excess moisture, not sensitive to ordinary dissolved polar materials. While the dielectric breakdown voltage can also be lowered by severe arcing, askael turns noticeably black or has particles of sooty carbon floating in it if arcing has occurred. Then the transformer should be repaired and the askael replaced.

If the dielectric breakdown voltage is checked periodically and decreases significantly, this indicates moisture pick-up, arcing, or both. When the dielectric breakdown voltage has dropped to 26 KV or less, an analysis for water is necessary. If water is found in excess of 40 ppm at room temperature, its source should be located and corrections made.

When the moisture content approaches 125 ppm (saturation level at room temperature), the dielectric breakdown voltage of askael drops below the value required for efficient insulating. The moisture content should not be allowed to rise over 70 ppm, sampled at operating temperature. If the moisture content is found to be in a satisfactory range and the dielectric breakdown voltage is low, the transformer manufacturer should be consulted.

Table IV shows the relationship of dielectric breakdown voltage vs. moisture and Table V indicates the approximate water solubility limits in askael and mineral oil.

Table IV
Relation of Dielectric Breakdown Voltage to Amount of Dissolved Water in Askael and Mineral Oil

Water Content (PPM)	Breakdown Voltage (ASTM D877)	
	Askael	Mineral Oil
0	70 KV	50 KV
20	65	39
40	47	30
60	40	26
80	38	22
110	10	5

0249297

9

Table V
Approximate Solubility of Water in Transformer
Askarel and Mineral Oil

°C	°F	Amount of Water (PPM) Dissolved	
		Askarel	Mineral Oil
30	82	8	8
20	64	16	10
10	50	28	12
0	32	41	20
-10	50	65	33
-20	68	94	56
-30	86	128	85
-40	104	170	130

XIV. Turbidity

may be the visual sign of undissolved water, or may indicate dirt. Cloudiness may also result from cold precipitation of an "incompatible" scavenger that was used in the earlier Pyralol transformers. This scavenger begins to come out of solution around 15°F above zero. To redissolve it requires heating to 150-200°F and agitation.

High dielectric breakdown voltage will quickly indicate that any turbidity present is not moisture; that the insulating efficiency of the askarel is still excellent. However, if the dielectric strength is below 25 KV, moisture should be determined, using the Karl Fischer method (ASTM D1533-60).

The dielectric breakdown voltage test for askarel serves primarily as an indicator for moisture. It is by far the most important maintenance test for transformer askarel.

XV. Check Points for Maintaining Askarel Insulation

A. General Considerations

Modern askarel transformers with welded construction or silicone or Viton gaskets (hand hole covers, switch and terminal compartment covers) and with properly constructed bushings require little or no maintenance. With properly constructed transformers, annual or semi-annual visual inspection and dielectric breakdown voltage test of the askarel fluid should suffice for routine maintenance checking over many years of service.

However, many askarel units were installed in the early 1930s—before the development of some of the better modern gasketing materials and before improved designs were developed for sealing out moisture. Such early units should be, and can be, modernized. Leaky or deteriorated gaskets should be replaced. If the askarel has become contaminated, it should be reconditioned. At the same time, a general clean-up of the unit and possible relubricating may be desirable.

If it is not convenient to take an old transformer out of service for general repairs, leaky gaskets can be sealed temporarily by painting over the leaky area with epoxy cement.

A survey of users indicates a good number of early-built askarel transformers (over 20 years old) are kept in continuous service in critical installations by the following steps (instead of modernization):

The operating units are equipped with compound pressure gauges for reading pressure above and below atmospheric. Positive

*Trademark of E. I. DuPont de Nemours & Company, Inc.

pressure is maintained on the seal by introducing nitrogen at 2 to 3 pounds. An atmosphere free for work men in the area daily inside the tank is also desired. If a sudden pressure drop is noted from nitrogen is introduced and the gaskets are checked for leaks with soap solution. Leaks are sealed by applying epoxy cement.

B. Modern Sealing Procedures

Transformer purchasers should specify the following modern technique for sealing:

1. **Welding Connections:** Covers, radiators, connections, switch and terminal housings, instrument connections, etc. should be welded.
2. **Bushing Connections:** A number of bushings have been developed to obtain a proper seal for the electrical connection through the tank wall. They are classified as follows:
 - a. **Welded Type:** (Bushing flange welded to tank wall)
 1. Cast resin bushing with a molded seal to the bushing stud and external stainless steel or copper flange.
 2. Rolled flange bushing with the metal to porcelain seal at the cap end flange made by being rolled into grooves in the porcelain over silicone rubber rings. The seal between the cap and stud is made by welding.
 3. Porcelain or glass bushings with metal to glass or metal to porcelain seals.
 - b. **Bolted Type:** (Bolted to tank wall)
 1. Cast resin bushings with either cast or metal flanges containing recessed gasket grooves.
 2. Porcelain or glass bushings with flanges containing recessed grooves or gasket stop.

The gaskets may be either of rectangular or circular cross section, usually 1/4 inch thick. Bushings with recessed grooves are suitable to use with cork, cork butyl rubber combinations or nitrile rubber as well as gasket materials such as silicone or Viton.

3. **Small Size Connections:** When not possible to weld, small size connection seals should be made with "Flexitallic" stainless steel rings. The surfaces must be machined and parallel. The filler between the steel laminations of the Flexitallic ring should be either silicone or Viton.
4. **Gaskets for Hand-Hole Covers:** Modern design specified silicone gaskets. Such gaskets must be retained in a groove. The groove preferably is machined into the flange or cover. However, it can also be formed by welding concentric steel strips to the flange of the cover. Generally the gaskets should be 5/16 to 1/2 inch thick for covers, depending on the depth of the groove or flange. A rectangular cross section is usually used.

The silicone material should be Dow Corning No. 50 Silastic[®] or equivalent. This is a low compression set material. For best sealing 20-25% compression is recommended with ample clearance in the groove or stop to allow for this compression.

No cement is required. With reasonable care the gasket is removable without damage and is reusable.

Silastic 50 is slightly swelled by alkali which contributes to the tightness of the seal. It is not deteriorated by alkali fluid or vapors. It resists weathering and it is thermally stable and

*Trademark of Flexitallic Gasket Company
 **Trademark of Dow Corning

flexible at all operating temperatures. It is an excellent moisture barrier.

NOTE: Dow Corning, Midland, Michigan will supply a list of Silastic 50 gasket fabricators to all transformer manufacturers or users. They will also furnish technical data. See Appendix K: Seals, Properties and Procurements.

C. The Older Sealing Arrangements

The older type gaskets consist of either cork or cork-nitrile rubber combinations or straight nitrile rubber.

1. Cork Nitrile Combinations: Covers for the main tank, hand holes, switch and terminal chambers, relief diaphragms, etc., are held in place by studs welded to the flange or by bolts. The gaskets are cut with openings and placed over the bolts. Often Shellac (Westinghouse Style No. 1150419, or General Electric Company's Glyptal* 1276) is used to cement the cork to the flange.

The following is recommended for sealing with the cork - nitrile rubber combinations:

Use Armstrong NC-767 cork-nitrile material or equivalent. The gasket can be cut from a single sheet or by scarfing strips of the material. A convenient method for joining strips is to make a Keystone Type joint. For this purpose, Westinghouse, Sharon, Pennsylvania, offers their gasket cutter Style No. 328 BG14 G01, (about \$15).

The joints -- and also the gasket -- should be cemented to the flange, using one of the above cements. Excess cement should not be allowed to reach the interior of the transformer.

After installation and bolting, the outside edge of the gasket should be coated thoroughly with epoxy cement to increase weather resistance.

This epoxy cement is a paste to which a curing catalyst is added immediately before use. Typical are:

- a. Epoxy Patch Kit #1C
Hysol Corporation, Olean, New York
 - b. Scotchcast** Resin #4
Minnesota Mining & Manufacturing Company
St. Paul, Minnesota
 - c. Adhesive A-1 and Activator Type B
Armstrong Products Company
Argonne Road, Walsaw, Indiana
 - d. Adhesive 9660-1, Synthetics Organic Company,
Cleveland, Ohio, used with activator diethylene triamine
(Corbide and Carbon Chemical Company)
2. Straight Nitrile Rubber: When straight nitrile rubber was originally used, invariably the gasket was recessed in a groove. This was to prevent gasket flow and to protect the material against excessive compression. Although this type seal was not cemented, the nitrile rubber gasket is not reusable.

Since grooves or stops have already been provided for the nitrile rubber seal, Silastic 50 can be easily substituted and is recommended. This conforms with modern practice.

XVI. Periodic Fluid Inspection and What Checkpoints Mean
On a regular schedule -- at six, nine, or twelve month intervals -- make a simple visual inspection of your spark and insulation and run a dielectric breakdown voltage check.

*Trademark of General Electric Company

**Trademark of Minnesota Mining & Manufacturing Company

A. Visual Inspection

Askarel is a clear, faint-yellow liquid. After long-term use this color may gradually intensify to light brown. The fluid should remain clear and free from turbidity or cloudiness.

Any color change - such as to a green, red or blue cast - indicates extraction of impurities (color materials) from the solid insulation. If a distinct foreign color pick-up is noted, check the complete range of electrical characteristics and notify the transformer maker. Blackening of the askarel may indicate an arcing condition. Other color changes alone are not danger signals since the dielectric breakdown voltage is not likely to be impaired.

B. Dielectric Breakdown Voltage

If the dielectric breakdown voltage has decreased significantly from the last inspection, or if it has gradually decreased below 20 KV range (at 26°C) - **RUN A CHECK FOR MOISTURE.** Use ASTM D1533 (Karl Fischer Method).

This dielectric breakdown voltage of askarel is the major indicator to the operating efficiency of your liquid insulation. Besides the visual inspection tests, dielectric breakdown voltage is the only test necessary to run on a routine basis. Well-sealed askarel transformers have service records of 25 to 30 years on the original askarel.

XVII. Inspection Checklist

1. If askarel is clear - even though darkened to light brown, has no sediment or turbidity, has dielectric breakdown voltage over 26 KV - give it the inspection "OK".
2. If askarel is clear, but has foreign color of blue, green, red ... It is "extracting color" from internal materials. This is not, of itself, an operating hazard when the dielectric breakdown voltage stays over 26 KV and moisture remains low. However, this rare occurrence calls for checking into the condition of the interior construction and consulting the transformer maker. However, when sampling the fluid care should be taken to avoid getting color into the askarel from paint that may be inside or outside of the sample valve.
3. If the moisture content is found to be above 70 ppm at operating temperature, then sampling should be done at more frequent intervals to establish a possible trend, particularly on outdoor installations.
4. If askarel is clear, but dielectric breakdown voltage drops to 22 or lower KV, and moisture rises over 80 ppm when sampled at operating temperature ... the askarel is ready for simple "refining". If the moisture is near the saturation level (about 125 ppm at room temperature) a thorough inspection should be made for "water droplets" in the transformer tank, and even for "globules" of water floating on the askarel surface. If found, the transformer manufacturer should be consulted for reconditioning both the transformer and the fluid.
5. If askarel is dark brown to black, if black particles of carbon are seen, and dielectric strength is low ... the askarel has been broken down by arcing. It cannot be refined and should be removed and incinerated under proper conditions. (See ANSI Committee C107 report on Use and Disposal of Askarel and Askarel-Soaked Materials, 345 East 44th Street, New York, New York 10017).

If any of these five simple inspection tests appear out of the ordinary or the relationship between appearance and test values is abnormal, contact your transformer supplier for a complete analysis.

Whenever a sample is to be shipped to Monsanto, please follow the directions shown under: "SAMPLING ASKAREL".

XVIII. Contamination in Transformers

Moisture, particulate matter, and aged decomposition products are known to be serious contaminating influences on transformer askarel.

The power factor test normally used for the detection of contamination in mineral oil filled transformers is of little use for this purpose in askarel filled transformers, due to the extreme effect of extraneous volatile polar materials. This increase in power factor is illustrated in Table VI has no adverse effect on dielectric breakdown voltage.

Table VI
Effect of Common Insulation Materials on Power Factor and Dielectric Strength
(Heat Aged 86 Hours in Askarel at 100°C.)

Material Immersed	Askarel After Exposure	
	Power Factor, Percent at 60 cyc., 100°C	Dielectric Strength 75°C
None (control)	1.0	35 KV
Black varnished cloth	85.0	42
Copper	1.6	40
Pressboard	2.0	37
Mantle paper	1.6	39
Phenolic formaldehyde resins	1.6	41
Shellac	8.0	36
Iron	5.0	38
Synthetic rubber	70.0	39

Similarly, trace contaminants from commonly used construction materials can lower the volume resistivity of askarel, without affecting its dielectric break-down voltage. This is shown in Table VII.

Table VII
Effect of Common Insulation Materials on Volume Resistivity of Askarel


Sample	Volume Resistivity $\times 10^9$ ohm cm (at 100°C, 500 Volts DC, 0.1 gpm)
1. New askarel before heat aging	2,000
2. New askarel after heat aging 86 hours at 100°C	1,900
3. After heat aging with 1 sq. inch specimens of:	
a. Phenolic resin tap changer material	1,200
b. Paper	750
c. Grade A pressboard (ten)	500
d. Grade A pressboard (gray)	500
e. Grade A pressboard, laminated strip	400
f. Cotton wrapping	300
g. Gypstal 1276 cement, cured 48 hrs. at 110°C	100

While trace contamination easily lowers volume resistivity from high levels, it is important to note that heavy contamination (as when arcing) does not lower the resistivity below the order of 10^9 ohm cm. at 100°C.

The different behavior of askarel vs. mineral oil in these respects can be summarized as follows:

High power factor and low volume resistivity in transformer mineral oils are commonly regarded as "danger signals" that the oil has deteriorated and broken down chemically or excessive moisture is present.

This is NOT TRUE of askarel liquid insulation unless the dielectric break-down voltage is low or the moisture content is high.



0249302

TOWOLDMON0027887

WATER_PCB-00012356

Manufacturers of oil and type transformers point out that it is quite well known that askarel transformers with initial power factor of the askarel fluid in excess of 80% at room temperature and 60 Hz are giving satisfactory service life. However, this leads to the assumption that both dielectric breakdown voltage and the stress are at satisfactory levels and do not show adverse trends.

XIX. ASTM Method For Investigating The Compatibility of Transformer Insulation and Construction Materials in Askarels

This method³ uses the change of electrical and/or chemical characteristics of transformer askarel resulting from its controlled exposure to insulation and construction materials, in order to evaluate their immediate major "contamination" effect on the askarel fluid. Delayed or long time contamination effects may not be detected.

The method also utilizes various physical tests on the insulation and construction materials after controlled exposure to the askarel to determine the compatibility of these materials with transformer askarel.

Properly proportioned specimens of the insulation or structural materials are immersed in refined askarel for 168 hours at $100 \pm 1^\circ\text{C}$ in a forced draft oven. Changes in electrical and chemical properties of the transformer askarel are compared against a control sample of the askarel treated in the same manner, in absence of the test specimens.

Dissipation factor (ASTM D 924) change is one of the criteria used. The askarel fluid is refined by an active treatment to a dissipation factor level of 0.05 max. at 100°C and 60 Hz and 0.01 max. at 25°C and 60 Hz. Corresponding values of the askarel fluid after heating 168 hours at 100°C in absence of a test specimen are 0.075 and 0.02 respectively. The maximum dissipation factor levels suggested for the askarel after heating in presence of the test specimen are 0.20 at 100°C and 60 Hz and 0.04 at 25°C and 60 Hz.

XX. Refining Askarel for Reuse

A. Filtering Through Dry Blotter Paper to Remove Moisture and Extraneous Particles

Most operators prefer portable refining apparatus, such as a plate press fitted with a dolly, available from Sparkler, Mundelein, Illinois or General Electric Company, Pittsfield, Massachusetts, or the cushion cartridge filter type, available from Industrial Filter Corporation, Lebanon, Indiana. Filter paper liners for the plate press are available from Carl Schleicher and Schuell Company, Keene, New Hampshire and manufacturers of filter presses listed above.

The filter paper must be dried immediately before use. For best results, spread the paper for maximum surface exposure in a hot air circulating oven and heat it for 4 to 6 hours at 110°C .

Circulate the askarel hot (but not over 40°C) through the filter fitted with the dry paper liners.

After filtration the dielectric breakdown voltage of the askarel should be 35 KV minimum.

1. Precautions: Filtering should not be done when the relative humidity exceeds 75%.
2. Any flexible hoses and gaskets on the refining equipment should be lined with or made of materials that will not be softened by contact with askarel fluid. (Materials lined with Silicone, Viton or Teflon, or flexible metal materials are suitable.)

³In process of publication by ASTM as of this writing.

⁴Trademark of E. I. DuPont de Nemours & Company, Inc.

Table VIII
Guide to Rate of Dissolved Water Removal
By Filtering Askarel Through a Paper Press

Passes Through Paper Press	Water in Askarel PPM
0	115
1	36
2	22
3	18
4	12
5	10
6	10

B. Disposal of Solid Wastes:

The ANSI Guide states that, "All Solid wastes which have been saturated with askarel should be disposed of by the following procedure:

1. The saturated wastes should be placed into leak-proof containers and transported to a supervised dry landfill site meeting State requirements. Alternatively, they can be disposed of by incineration in State approved facilities.
2. Solid absorbents used for spills can be disposed of uncontained in the supervised dry landfill site; transport to the site should be in closed containers. Alternatively, incineration can be used in accordance with par. B (See Section 4 for facilities)."

C. Solid Insulation Requiring Drying:

If the solid insulation of the transformer requires drying, consult the transformer manufacturer or an apparatus service shop, as in such case oven drying is preferred.

D. Earth Treatment for Maximum Improvement of Power Factor and Volume Resistivity:

We question whether pumping and filtering the fluid solely to achieve a change in power factor or volume resistivity alone is justified in today's ecological climate regarding PCBs. We recommend that in these situations the original transformer manufacturer be contacted.

1. Procedure:


The askarel liquid should be relatively dry prior to the following earth filtration.

As a coating on the filter paper surface use finely divided Attapulgus clay or Fuller's earth dried and activated by heating for 12 hours at 300-350°F immediately prior to use. The amount of earth used should be 0.1 to 0.2 percent by weight on the weight of the askarel to be treated. Askarel weighs about 12.6 pounds per gallon.

To deposit the earth evenly, stir one third of the earth with a small portion of askarel in a clean container. Pump the mixture through the filter and follow with two more one third portions. Then circulate askarel taken from near the top of the transformer, pass it warm (not over 55°C) through the earth-coated filter and feed back through the bottom transformer outlet. Continue circulation until the fluid is clear and test shows that the electrical properties are fully restored.

2. Effect of Earth on Removal of Scavengers

Only slight and insignificant loss by selective absorption of tin tetraphenyl and epoxides occurs when askarel is refined by treatment with 0.1 to 0.2 percent by weight of earth. To remove significant amounts of the scavengers requires repetitious treatment with much larger amounts of earth.



0249304

Table IX
Approximate Relationship Showing the Insignificant
Effect of Power Factor and Volume Resistivity on
Dielectric Breakdown Voltage of Transformer Askarel

Power Factor (60 cyc.)		Volume Resistivity x 10 ⁹ ohm cm (at 100 C, 500 Volts DC, 0.1" gap)	Breakdown Voltage 25°C, 0.1" gap
100°C	25°C		
2%	0.05%	1500	36 KV
55%	0.1%	500	36
15%	0.7%	100	36
20-25%	2.0%	50-70	35
40-50%		25	35

XXI. Cleaning Arced Transformers

If a unit has arced so that the askarel is no longer fit for use, a thorough cleaning of the unit is necessary before refilling with new askarel insulation and returning it to service*. Follow this procedure:

- A. Drain out all dark, carbon contaminated askarel. Arrange to have the scrap fluid incinerated under proper conditions. (See ANSI Committee C107 report.)
- B. Carefully brush carbon deposits from internal parts and insulation, using a soft bristle brush making sure that insulation is not damaged.
- C. Flush thoroughly using new askarel — *not* an oil, *not* a cleaning solvent.
- D. Flush a second time with fresh askarel; drain; then fill to the proper level with new askarel.
- E. Energize transformer to warm the fluid for 24 to 48 hours; then circulate the askarel through a filter, returning it to the unit filtered and ready for use.

*This assumes that the cause of arcing has been established and corrections made. When severe arcing occurs, major repairs are usually necessary and the unit rebuilt. This procedure can be applied for flushing out the repaired units.

XXII. Sampling Askarel

Take a sample as close to the top of the liquid surface as possible. Many large askarel transformers have a built-in sampling tube near the surface for convenient sampling. Then, to make sure that your sample truly represents your askarel insulation, take another sample from the bottom. If additional sampling tube connections are contrived on the valves for easier sampling, make the tubes of clean glass, stainless steel, aluminum or tin for rigid types; and silicone, or Viton or Teflon tubing for flexible types.

Use NEW containers for the askarel sample. A new and thoroughly pre-dried, small-mouth quart glass bottle fitted with a Bakelite® screw cap with aluminum or tin cap liner is recommended for quick, on-site testing. (If complete analysis is to be made, a 5-pint size sample is required.)

Be sure that the new bottle does not stand open to collect dust or moisture. Rinse the sample bottle and cap lining two or three times with askarel from the transformer, then fill it. If the sample will be tested promptly, a clear glass bottle can be used. If sample is to be stored indefinitely, use an amber glass bottle or wrap clear glass with aluminum foil.


- A. Select a dry day. Do not sample insulation on a warm, moist day when humidity exceeds 75%, and

*Trademark of Union Carbide Corporation

- B. Make sure that the askarel is as hot as warm as the surrounding air. (Cool liquids can condense moisture from humid air.)
- C. When sampling askarel from transformers, it is best to take the sample when the unit is warm and operating at average or maximum load, especially for a check on moisture as reflected by a dielectric breakdown voltage test. Sampling the warm askarel more truly represents its condition during operation.

Experience shows that water will migrate from a transformer's solid insulation to the askarel liquid and vice versa, depending on temperature. Therefore, when the transformer is hot, the moisture is most likely to be found in the liquid. This accounts largely for periodic variations in dielectric breakdown voltage. For example, a relatively high dielectric breakdown voltage may be found during winter months and a relatively low dielectric breakdown voltage during the summer months on samples taken from the same unit.

When testing has been completed, the remainder of the fluid sample should be destroyed by high temperature incineration described in Section VIII.



Section 1B Askarel Filled Switches and Terminal Chambers

I. Introduction

High voltage leads are usually connected to askarel or mineral oil filled network transformers and power centers through terminal chambers and switches. In some cases terminal chambers are not used, and the high voltage leads are connected directly to the switch terminals. They may be filled with either askarel or mineral oil. Switches are usually rotary or drum type fitted with a revolving block and porcelain unit as the principal element arranged for three phase service.

Askarel transformers with attached switches have been in use for about 20 years. When they were first introduced, the availability of insulating and gasketing materials was rather limited and even the best materials at the time had no service history. As a result, inadequate gasketing materials such as cork, nitrile rubber, and nitrile rubber and cork particles were used. While satisfactory for a limited period of time, these materials cannot be depended upon for the expected long life of the equipment.

The terminal chamber is usually above or below the switch compartment and separated by a steel wall through which the bushings are inserted. When bushings are properly selected and correctly installed, there is no leakage from one compartment to the other. With poor bushing seals, and the terminal chamber above the switch, potting compounds or cable oil can seep into the askarel. When the terminal chamber is below the switch, askarel can drain into the terminal chamber.

II. Sources of Contamination

There are three possible sources of contamination for askarel in switches and terminal chambers, they rank in this order of frequency, (1) water entering through poor gaskets, (2) decomposition products from arcing when switch is used to break magnetizing current, (3) entrance of pothead or cable compounds through leaky bushing seals.

Unlike an askarel transformer where the amount of contamination is likely to be very small (probably only trace amounts) in relation to the volume of askarel fluid. In switches or terminal chambers with faulty seals, the amount of contamination can be relatively large.

Experience has shown that, based on the number of installed askarel switch units, the percentage of failures is extremely small. When investigated, it has been found that most failures originate in the switch chamber. Water is the chief source of contamination. However, heavy contamination of askarel with petrolatum and asphalt material, due to leakage, have caused a few failures.

Petrolatum is used frequently for filling terminal chambers. When either cable oil or petrolatum seeps into askarel, no great harm results. The line resistance will be somewhat decreased and power factor of the askarel will increase with an accompanying drop in resistivity. While highly undesirable, it is doubtful that failure of the unit results. Where asphaltic compounds are used in place of petrolatum, the danger is increased somewhat because asphaltic contamination may cause excessively high dielectric losses in the askarel.

When the terminal chamber is below the switch chamber, the potting compound can be contaminated by askarel if the bushing seals are leaky. This is undesirable because the askarel will increase the power factor and conductivity of the potting compound or cable oil and develop heat from dielectric loss. If this mixture is drawn into the cable

Insulation, a case failure & the use of both compounds the advantages of Askarel become evident.

III. Sealing, Switches and Terminal Chambers

Proper bushing construction, use of Silicone seals and welding wherever possible is highly desirable (as required in Section A) where an elastomeric seal is to be used in contact with both Askarel and Petroleum oil, DuPont's Viton is suggested.

For new equipment the user should specify these modern sealing arrangements to keep out contaminants and minimize maintenance.

IV. Askarel Used Under Mild Arcing Conditions

The IEEE Guide for Transformer Askarel calls attention to the following:

"Askarel is used, to some extent, in apparatus where it is subjected to light intermittent arcing, such as in self-contained induction regulators, where operating switches are continually producing slight arcs, in transformer deenergizing switches, etc. Under normal conditions, deterioration of the Askarel is very slight. However, improperly adjusted or defective switches in this type of apparatus can produce excessive and prolonged arcing and accelerated deterioration of the Askarel. It is recommended that when Askarel is used under these conditions, checks of the liquid, especially for moisture and dielectric breakdown voltage, made more frequently than when it is used only as a cooling and insulating fluid. Deterioration of this type is indicated by a blackening of the liquid. It can usually be reconditioned as previously described. Special attention should be given to maintaining the level of the liquid at the appropriate concentration."

V. Maintenance for Askarel Filled Switches

- A. Switches used for grounding after power source has been deenergized will not undergo arcing.
- B. Switches interrupting magnetizing current will be subject to arcing. The amount of decomposition will depend on power interrupted, time and frequency of operation. As a general rule, the liquid should be checked after 5 to 10 operations.
 1. On newly installed switches, check the Askarel at 3, 6 and 12 month intervals; if found satisfactory, check once annually thereafter. With proper attention to the gasketing of covers and bushings, experience will probably indicate that less frequent inspection is warranted.
 2. Check Askarel for:
 - a. Dielectric breakdown voltage (ASTM D877): It should be 26 KV minimum. If dielectric breakdown voltage is low, confirm presence of water by Karl Fischer method ASTM D 1533. Filter to remove moisture. Dielectric strength should then be 30 KV minimum.
 - b. Presence of carbon from arcing. Fluid should be relatively free of carbon. If badly arced and very black, replace fluid. If only minute amounts of carbon are present, filtration is recommended. Check power factor of liquid (should not be over 5% at 25°C and 60 cycles). Flush out switch chamber with several gallons of fresh Askarel before refilling.
 3. If there is discoloration, high power factor, detectable change in specific gravity or refractive index, or if fluid flashes below 260°F, there is a possibility of seepage of potting compound into the switch compartment. In this case, correct any leaky bushing seals with proper replacement and fill with new Askarel.
 4. If terminal chamber is below switch, check potting compound for presence of Askarel (can usually be detected by odor or by an increase in specific gravity). If Askarel is present, correct any leaky bushing seals with proper replacement and renew compound.
 5. Examine cover gaskets visually. Deterioration can be detected


- by swelling and cracking of the exposed edge. In cases of severe deterioration, liquid seepage is usually present.
6. Check for leakage at packing gland of switching shaft. If leaking, repack with a Silastic ring type gasket.

VI. Askarel Under Excessive Temperature or Fault Conditions

The IEEE Guide also points out that:

"Chlorobenzene used in transformer askarels begin to boil at temperatures of about 205°C under atmospheric conditions. If the material is heated to such high temperature in a sealed system, pressure develops. Pressure will also develop in the system if the askarel is arced sufficiently to generate copious hydrogen chloride gas.

"Therefore, it is recommended that wherever possible, sealed askarel-filled equipment be provided with pressure relief devices. These devices must be large enough to provide immediate relief at a definite pressure, and to prevent further build up of pressure if decomposition continues. It must be remembered that the presence of devices of this sort does not necessarily preclude the rupturing of containing vessels, since pressure build up can be extremely rapid under violent arcing conditions."



0249309

21

TOWOLDMON0027894

WATER_PCB-00012363

Section C Analytical Services on Transformer Askarel Available From Monsanto

Transformer users not wishing to make their own fluid analyses can obtain the service from Monsanto. Simply contact Monsanto and specify what analyses are wanted. You will be sent the proper sized, clean sample container, fitted with a proper label. When you receive this, carefully take your sample (following the procedure for sampling in this guide). Send the container to Monsanto's laboratory. Charges listed include sample container, shipping, handling and laboratory costs.

Types of Analyses Available

Analysis 1)

ROUTINE MAINTENANCE CHECK

Total Charge: \$25.00

To determine the general condition of the fluid and find whether further analysis is necessary. (one-quart sample required)

Properties Tested

Dielectric Breakdown Voltage

Color and Condition

Moisture

You will be notified of the results of this test. If further testing is indicated, and you want a complete analysis, you will be sent a five-pint sample container. This sample will be used for the following series of tests:

Analysis 2)

COMPLETE ANALYSIS

Total Charge: \$55.00

(1) To determine the extent of fluid contamination, (2) earth refinement to determine what degree of restoration of electrical and insulating properties is possible, (3) check test to see how the fluid responded to earth treatment.

a) Complete Analysis: to determine the extent of contamination

Properties Tested

Free Chlorides

Color and Condition

Acidity

Specific Gravity

Dielectric Breakdown Voltage

Refractive Index

Power Factor, Dielectric Constant, and Resistivity

Water

b) Earth Refinement Response:

Consists of treatment for 2.5 hours at 50-60°C. with 0.1 to 0.2 percent by weight of properly conditioned Attapulgus clay and then filtration through dry filter paper.

c) Analysis After Laboratory Earth Refinement:

Properties Tested

Acidity

Refractive Index

Dielectric Breakdown Voltage

Water

Power Factor, Dielectric Constant, and Resistivity

Free Chlorides

You will be notified of the results of this test series on your sample. Then after refining your entire transformer fluid fill you can check on the results by requesting the following analysis:

Analysis 3)

ANALYSIS AFTER EARTH REFINEMENT

Total Charge: \$35.00

(This charge will not apply when analyses 1 and 2 have already been made.)

To determine whether the entire lot of the askarel fill responded to the same extent as the laboratory sample. (five-pint sample required)

Properties Tested

Free Chlorides

Color and Condition

Acidity

Refractive Index

Dielectric Breakdown Voltage

Water

Power Factor, Dielectric Constant, and Resistivity

To arrange for the tests described above write to the following address:

Paul G. Benignus
Monsanto Company
800 North Lindbergh Blvd.
St. Louis, Missouri 63166

Samples to be tested should be clearly marked for identification and sent directly to:

Monsanto Chemical Company
W. G. Krummrich Laboratory
Sauget, Illinois 62201
Attention: R. Kusler

22

0249310

TOWOLDMON0027895

WATER_PCB-00012364

Appendices

APPENDIX A

Askarel Stability and Composition of Arc-Formed Gas: Askarel insulation is one of the most inert, chemically stable heat resistant, non-corrosive liquids known. It will not break down, oxidize or sludge when exposed to air and high temperatures, 150°C. or even somewhat higher. Arcing, however, will break down the compound to liberate some hydrogen chloride and small amounts of carbon.

APPROXIMATE COMPOSITION ARC-FORMED GAS FROM TRANSFORMER ASKAREL BLENDS ASTM TYPES D AND G (INERTEN 70-30 AND PYRANOL A1303B-3, RESPECTIVELY)

Gas	Amount
Carbon monoxide	0.3%
Carbon dioxide	0.3%
Oxygen	0.6%
Inert gases	1.5%
Hydrogen chloride	97.3%
(note the absence of phosphine)	

This arc-formed gas from ASTM Type D and Type F transformer askarels is non-flammable and non-combustible.

For all practical purposes, the amount of gas liberated from askarel under a given set of arcing conditions is about 100 cubic centimeters per kilowatt-second.

APPENDIX B

SOLUBILITY OF GAS IN TRANSFORMER ASKARELS ASTM TYPES D AND G

	Percent of Gas By Volume Corrected to			
	25°C 760 mm		0°C 760 mm	
	25°C	100°C	25°C	100°C
Carbon dioxide	71%	47%	—	—
Air	5.7	4.9	5.8	5.0
Nitrogen	6.0	4.6	5.5	4.4
Hydrogen chloride ¹	37.8	50.9	—	—

¹In absence of scavenger

APPENDIX C

EFFECT OF TEMPERATURE ON DIELECTRIC BREAKDOWN VOLTAGE OF ASKAREL

Temperature °C	Dielectric Breakdown Voltage ASTM D877
-60	67 KV
-40	63
-20	57
0	51
20	50
40	50
60	48
80	45

0249311

23

APPENDIX D

COMPARISON OF THE APPROXIMATE VISCOSITY IN SAYBOLT UNIVERSAL SECONDS OF TRANSFORMER ASKARELS AND MINERAL OIL

Temp. °C	Pyranol A13838-3	10-C Mineral Oil	Inerteen 70-30
-20	1000	1000	2800
0	100	150	195
20	70	85	85
40	45	49	50
60	39	40	40
80	34	34	36
100	30	30	33

APPENDIX E

THE DENSITY OF INERTEEN 70-30 AND TRANSFORMER PYRANOL A13838-3 Approx. Density gm/cc.

Temp. °C	Inerteen 70-30	Pyranol A13838-3
0	1.674	1.677
20	1.662	1.666
40	1.629	1.632
60	1.607	1.610
80	1.485	1.488

APPENDIX F

The thermal conductivity values of transformer Pyranol A13838-3 at 27°C and 58°C are 26.2 and 26.8×10^{-5} calories centimeters⁻², degrees centigrade⁻¹, second⁻¹, respectively. Or, approximately 0.06 BTU per (hr.) (sq. ft.) (°F.) per foot. This same approximation applies to Inerteen 70-30.

APPENDIX G

Heat Capacity

Over the temperature range of 25° to 125°C the specific heat of transformer askarel is close to 0.30 calories per gram per degree.

APPENDIX H

Coefficient of Expansion

The average coefficient of expansion of transformer askarel over the temperature range 20 to 100°C is 0.0007 cc/cc/°C. One gallon would increase to 1.056 gallons on heating from 20 to 100°C.

APPENDIX I

Fire Resistance

Askarels of various compositional types are used. Under arcing conditions the gases produced, while consisting of predominantly non-combustible hydrogen chloride can yield varying amounts of combustible gases depending upon the askarel type.

Insulation systems incorporating these askarels and cellulosic or other organic materials may, when arced, produce gaseous mixtures which are moderately flammable. As a precaution, such gases should be removed from the askarel by bubbling dry nitrogen through the askarel and flushing the gas space with dry nitrogen before any work is performed on the apparatus.

APPENDIX J

Seals, Properties and Procurement

Dow Corning Corporation, Midland, Michigan with Districts at Atlanta, Boston, Chicago, Cleveland, Dallas, Los Angeles, New York City, Washington, D.C. and Toronto has available Bulletin D9-019, August 1962 entitled "Silastic Design Data". This lists the gasket fabricators throughout the country from whom the "Silastic 50" gasketing can be purchased in sheet, extrusions or molded shapes.

Generally, Silastic 50 sheet goods are stocked by local die cutters, hence, could be generally purchased locally. Usually small quantities of gaskets are die cut. If larger quantities are needed, tools are made of the same type used to cut other elastomers.

Where the gasket is extruded for fitting into a machined groove or between gasket stops, Dow Corning advises use of a scarfed joint. This joint is then cemented using Dow Corning's Silastic 140 (clear) or their RTV 731 (white) materials, which air cure.

Dow Corning points out that the local "rubber" fabricators purchase the Silastic 50 in billet form. This is worked on a roll mill in preparation for sheeting or extrusion. Then to obtain the desired physical properties the fabricator must oven cure the Silastic 50 for 24 hours at 480°F.

SPECIFICATIONS*

	Color	White
ASTM D676	Specific Gravity at 77°F	1.20 ± 0.02
ASTM D412	Hardness, Shore A, Scale	45 to 60
ASTM D412	Tensile Strength, psi, min	800
ASTM D395	Elongation, percent, min	250
	Compression Set after 22 hrs at 300°F, percent, max	30

*All physical properties measured on 0.075 inch thick samples molded 5 minutes at 240°F, and oven cured 24 hours at 480°F.

APPENDIX K

Caution Label

The following or equivalent caution statements should be fixed on all containers of transformer askarels and the transformers themselves:

This product contains Polychlorinated Biphenyls (PCBs). Care should be taken to prevent entry into the environment through spills, leakage, use, vaporization, or disposal of liquid or containers. Avoid prolonged breathing of vapors or mists. Avoid contact with eyes or prolonged contact with skin. If skin contact occurs, remove by washing with soap and water. Following eye contact, flush with water. In case of spillage onto clothing, the clothing should be removed as soon as practical, skin washed, and clothing laundered.

Monsanto

MONSANTO INDUSTRIAL CHEMICALS COMPANY
SPECIALTY PRODUCTS GROUP
800 N. LINDBERGH BLVD.
ST. LOUIS, MISSOURI 63166

The information herein regarding obtaining optimum results from askarel fluids in your transformer has been accumulated by Monsanto for over 40 years from the experience of makers and users of askarel transformers and it is believed will be helpful.

Nothing herein shall be construed as applying to other than askarel insulation. Data and maintenance suggestions herein do not apply to the other components of the transformer. All operating and maintenance suggestions recommended by the manufacturer of the transformer should also be carefully followed.

Because these maintenance directions apply only to the askarel insulation, Monsanto disclaims any liability for damage to property or injury to persons arising from transformer operation.

0249313

) 25

TOWOLDMON0027898

WATER_PCB-00012367

CUSTOMER SERVICE CENTERS

AKRON, OHIO 44313

260 Springside Drive
Montrose Development Park
Tel. (216) 656-4111

ATLANTA, GEORGIA 30339

320 Interstate North Parkway
Suite 600
Tel. (404) 432-7111

BOSTON, MASSACHUSETTS 02149

Everett Station
Tel. (617) 387-5010

CHICAGO, ILLINOIS

3159 Des Plaines Ave.
Des Plaines, Illinois 60018
Tel. (312) 290-6688

CINCINNATI, OHIO 45236

8041 Holbrook Road
Tel. (513) 904-1100

DETROIT, MICHIGAN

500 Northland Towers West
Southfield, Michigan 48076
Tel. (313) 357-0510

HOUSTON, TEXAS 77027

1301 Post Oak Tower
5051 Westheimer Road
Tel. (713) 621-9550

LOS ANGELES, CALIFORNIA 90022

6670 E. Jolita St.
Tel. (213) 723-2492

NEW YORK, NEW YORK 10036

1114 Avenue of the Americas
Tel. (212) 764-5000

ST. LOUIS, MISSOURI 63166

800 N. Lindbergh Blvd.
Tel. (314) 694-1000

SAN FRANCISCO BAY AREA

2710 Lafayette
Sante Clara, California 95052
Tel. (408) 243-0414

SEATTLE, WASHINGTON 98121

2112 Third Avenue
Tel. (206) 622-4203

WILMINGTON, DELAWARE 19810

Suite 204, Bancroft Bldg.
3411 Silverdale Road
Tel. (302) 478-4600

Monsanto Industrial Chemicals Co.

A Unit of Monsanto Company

800 N. Lindbergh Blvd., St. Louis, Mo. 63166

Monsanto

0249314

2-2438-1273-S Litho. in U.S.A.

TOWOLDMON0027899

WATER_PCB-00012368