IEEE

This Guide No. 76 has been printed April 1974

GUIDE

FOR

ACCEPTANCE AND MAINTENANCE OF TRANSFORMER ASKAREL

IN EQUIPMENT

MCNS 075343

ACKNOWLEDGEMENT

The Institute wishes to acknowledge its indebtedness to those who have so freely given their time and knowledge, and have conducted experimental work on which many of the I.E.E.E. publications are based.

The work of preparing the Guide was carried out by members of the Insulating Fluids Subcommittee of the I.E.E.E. Transformers Committee. The members of the subcommittee are:

E. L. Raab, Chairman

P. G. Benignus
G. L. Blenkle
J. E. Dind
D. A. Gillies
C. Keil
A. H. Locke
R. I. Lowe
W. H. Meade*
E. L. Morrison
V. R. Mulhall
J. C. Parker
P. S. Pugh
W. C. Reinhardt
R. L. Schwab
T. K. Sloat
~~R. K. Stout~~

*Deceased

MONS 075344

CONTENTS

		Page
I	Introduction	4
II	Askarel - General Characteristics	4
III	Evaluation of Askarel Received in New Equipment	5
IV	Classification of Service Aged Askarel	6
V	Economic Factors	7
VI	Sampling	8
VII	ASTM Askarel Tests and Their Significance	8
VIII	Testing Procedures	12
	A. Field Screening B. Laboratory Screening	
IX	Reconditioning and Reclaiming Service Aged Askarel	12
	A. General B. Treatment After Exposure to an Arc C. Filtering Through Dry Blotter Paper to Remove Moisture and Extraneous Particles D. Fuller's Earth Treatment for Maximum Improvement of Power Factor and Volume-Resistivity E. Addition of Scavengers	
X	Handling Materials	14
XI	Askarel Used Under Mild Arcing Conditions	15
XII	Askarel Under Excessive Temperature or Fault Conditions	16
XIII	Recommended Handling Precautions	16
XIV	Storage and Handling and Disposal	17
	A. Drums B. Tank Cars C. Sampling D. Effect of Light Exposure E. Disposal	
XV	Underwriters' Laboratories Reports	17
XVI	Appendix - Results of Survey of Major Users of Transformer Askarel	18

ASTM methods referred to in this Guide are obtainable at Headquarters of the American Society For Testing and Materials at 1916 Race Street, Philadelphia 3, Pa.

MONS 075345

GUIDE

OF THE

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS

ACCEPTANCE AND MAINTENANCE OF TRANSFORMER ASKAREL IN EQUIPMENT

I INTRODUCTION

The term askarel generally describes a widely used, broad class of non-flammable synthetic halogenated hydrocarbon insulating liquids. In this Guide, it applies solely to askarel in transformers, reactors, and accessory equipment operated at power frequencies.

B, 2nd ¶ →

Insert A

Askarel contained in such apparatus as received from the manufacturer but prior to service operation should exhibit certain properties in order to insure satisfactory performance. It should be expected that askarel properly sampled from such equipment usually exhibits characteristics somewhat different from those obtained on new askarel which has not been in contact with apparatus constructional materials. Experience has indicated that variation of some characteristics of the askarel will not impair the service life of the equipment.

However, certain essential properties must be retained if askarel is to perform reliably its dual role of electrical insulation and heat-transfer agent.

It must have adequate dryness and a dielectric strength sufficient to withstand the electric stresses imposed in service. It must retain a sufficiently low viscosity so that its ability to circulate and transfer heat is not impaired. It should not be allowed to become so deteriorated or contaminated that it adversely affects the operation of the apparatus.

This guide assists the power equipment operator in evaluating askarel as received in transformers, reactors and accessory equipment operated at power frequencies and in his efforts to maintain askarel in serviceable condition. It recommends standardized tests and evaluation procedures. Methods are outlined for reconditioning and reclaiming askarel whenever necessary.

II ASKAREL - GENERAL CHARACTERISTICS

Commonly used transformer askarel consists of chlorinated aromatic hydrocarbons, and unlike mineral insulating oil is not subject to oxidation, is non-flammable, and is incapable of evolving explosive gases when decomposed by an electric arc. Consequently, data obtained from flash and fire point testing require somewhat different interpretation for the two fluids.

Insert A
Insert B

MONS 075346

Askarels of various compositional types are used. Under arcing conditions the gases produced, while consisting of predominantly non-combustible hydrogen chloride can yield varying amounts of combustible gases depending upon the askarel type.

Insulation systems incorporating these askarels and cellulosic or other organic materials may, when arced, produce gaseous mixtures which are moderately flammable. As a precaution, such gases should be removed from the askarel by bubbling dry nitrogen through the askarel and flushing the gas space with dry nitrogen before any work is performed on the apparatus.

material

In comparison to mineral insulating oil, askarel is a relatively polar mineral; i.e., its molecules are dipoles, free to rotate around their axes and responsive to orientation by electrical forces. Askarel also exhibits a much higher dielectric constant and capacitance than insulating oil, and these differences must be kept in mind when interpreting electrical test data.

Because it is relatively polar, and possesses high solvency power, askarel is much more electrically sensitive to trace contaminants than insulating oil, and consequently the choice of constructional materials destined for use in askarel is very critical. This sensitivity is reflected in the power factor and resistivity (specific resistance) of the askarel.

It is important to note that, with the exception of water, the dielectric breakdown voltage of askarel is not generally adversely affected by many of the contaminants to which its power factor and resistivity (specific resistance) are so sensitive. In fact, the dielectric breakdown voltage of askarel is somewhat greater than that of insulating oil. Therefore, the values assigned these dielectric fluids in newly supplied transformers are 30 kV min. and 26 kV min., respectively.

As with insulating oil, askarel must be kept dry. It can pick up moisture from exposure to humid atmosphere. Under similar conditions of exposure, askarel can pick up nearly twice as much moisture when measured on a parts per million weight basis.

A final obvious difference is that askarel is about one and one half times as heavy as water, whereas mineral oil is lighter than water. This means that any free water present will float on askarel whereas free water in oil will be at the bottom.

III EVALUATION OF ASKAREL RECEIVED IN NEW EQUIPMENT

Some users of askarel equipment find it desirable to make "as received tests" on all equipment. It is quite common to use the dielectric breakdown voltage test and visual appearance as the most significant tests. If suitable equipment and trained personnel are available additional information may be obtained from the power factor, color, and moisture content tests.

In sampling askarel contained in apparatus extreme care must be exercised in order to obtain a representative sample. ASTM Method D 923 should be followed.

New equipment with askarel exhibiting the following characteristics is considered acceptable:

		ASTM Methods
Dielectric Breakdown Voltage	30 kV min.	D 877
Color	300 max. (Straw color)	D 2129
Condition - Visual	Clear	D 1702
Water Content	35 parts per million max.	D 1533
Power Factor at 25C	*	D 924, D 150

MONS 075348

*The power factor of askarel taken from new transformers, reactors and accessory equipment can reflect the presence of moisture, dissolved polar compounds, or other contaminants and may vary with the type of equipment from which the sample was taken due to the different ratios of liquid-to-solid insulation and to the high solvency power of the askarel. Given an acceptable water content and dielectric breakdown voltage of the askarel as indicated above, a high power factor seldom impairs the serviceability of the askarel within rather broad limits and is indicative of the degree of contamination present.

Recognizing the possibility of a wide range of power factors being recorded for askarel in new equipment, it is difficult to establish a single limit which would be acceptable to both suppliers and users for all applications. However, as a broad guide, power factors up to about 10% at 25C and 60 cycles per second (hertz) do not in general indicate any abnormal contamination providing that the other criteria (water content, dielectric breakdown voltage, etc.) are met. Much higher power factors may indicate excessive contamination or the misapplication of the solid materials used in manufacture in contact with the askarel and should be investigated.

The significance of the foregoing and other tests listed in this guide are discussed in Section VII.

IV CLASSIFICATION OF SERVICE AGED ASKAREL

It is extremely difficult, if not impossible, to indicate the value of specific tests and recommended test limits for all possible existing applications of askarel. It should also be recognized that with the present state of knowledge no one test can be used as the sole criterion of condition of askarel. It is possible, however, to summarize the value and importance of current tests and to suggest methods of treatment for the askarel being examined, such methods being based on current industry experience. Askarel may be placed in the following classifications based upon composite evaluation of significant characteristics and on field and laboratory screening tests.

Group I

This group contains askarel which is in satisfactory condition for continued use.

Group II

This group contains askarel which requires only minor reconditioning for further service. (Reconditioning is the removal of moisture and insoluble contaminants. The usual method employed is filtration.)

MONS 075349

Group III

This group contains askarel in poor condition. It should be reclaimed or discarded depending upon economic considerations. (Reclamation involves the use of methods and processes which result in a purification of the askarel. Treatment with an adsorbing agent such as fuller's earth is most widely used.)

Group IV

This group contains askarel in such poor condition and requiring such drastic treatment that it is not feasible either technically or economically to attempt reclamation. Examples of such a condition would be a severely arced or excessively oil contaminated askarel.

V ECONOMIC FACTORS

In this section of the Guide, askarel is classified on the basis of significant characteristics. Many of the undesirable characteristics of used askarel can be corrected by reconditioning or reclaiming, if economic conditions justify it. The alternate choice is to replace with new askarel.

A review of the experiences of many users of electric equipment reveals a wide variation in the actual cost data involved in the reconditioning or reclaiming of askarel. This variation can be attributed to the amount and condition of askarel involved, laboratory and shop facilities, whether the work is performed at one central or several distant locations and the availability of qualified personnel.

Askarel that contains water and insoluble contaminants can be reconditioned by mechanical means using various filter devices. If soluble and/or colloidal contaminants are present in the askarel, reclaiming can be done with special filtering devices or a special filter press using a material such as fuller's earth.

To determine if reconditioning or reclaiming of askarel is economically justifiable, a number of factors must be considered. Some of these factors are as follows:

1. Value of askarel being considered for processing
2. Cost of processing materials
3. Total cost of process vs. quality of end-product
4. Equipment maintenance and amortization
5. Cost of collection and storage
6. Labor and transportation costs
7. Laboratory cost
8. Loss of askarel during processing
9. Cost of scavengers and make-up of chemicals if addition is necessary and desirable
10. Cost of disposing of processing material and scrap askarel
11. Cost of new askarel delivered at job site

MONS 075350

VI SAMPLING

Representative samples, whether of the complete contents or only parts thereof, are extremely important from the standpoint of evaluation of the quality of the product sampled. Obviously careless sampling procedure or contamination in the sampling equipment will result in a sample that is not truly representative. This generally leads to erroneous conclusions concerning quality and incurs loss of time, effort, and expense involved in securing, transporting, and testing the sample. It is strongly recommended that all of the procedures and precautions outlined in the latest revision of ASTM D 923 (Sampling Electrical Insulating Liquids) be followed.

Because of the high specific gravity (relative density) of askarel (greater than 1), water and some other impurities are most likely to be found at or near the surface. The top sample, therefore, is considered to represent the worst condition.

VII ASTM ASKAREL TESTS AND THEIR SIGNIFICANCE

There are a number of tests that can be applied to askarels as a basis for their classification as indicated in the foregoing. It is recommended, wherever possible, that tests be the latest revisions accepted as standards or tentatives by ASTM. These tests and their significance are as follows:-

		ASTM Methods
1.	Color	D 2129
2.	Dielectric Breakdown Voltage	D 877
3.	Flash and Fire Point	D 92
4.	Inorganic Chlorides	D 1821
5.	Neutralization Number	D 974, D 664
6.	Pour Point	D 97
7.	Power Factor	D 924, D 150
8.	Refractive Index	D 1807
9.	Resistivity (Specific Resistance)	D 1169
10.	Scavenger Content	D 1701
11.	Specific Gravity (Relative Density)	D 1810
12.	Viscosity	D 88, D 445
13.	Visual Examination of Service Aged Askarels in the Field	D 1702
14.	Volume of Oil in Oil-Contaminated Askarel	D 1808
15.	Water Content	D 1533

1. Color - D 2129

The color of askarel is a numerical value based on comparison with a series of numbered color standards with transmitted light under prescribed conditions. Color is chiefly significant as an indicator of contamination in askarel. Frequently this contamination is the result of solvent action between the askarel and other materials in the apparatus involved. No definite relationship can be established between color and the physical and electrical characteristics of the liquid.

MONS 075351

2. Dielectric Breakdown Voltage - D 877

The dielectric breakdown voltage of askarel may be defined as the voltage at which electrical breakdown of the material occurs under prescribed conditions. The dielectric breakdown voltage of askarel is of importance as a measure of its ability to withstand electrical stress without failure. It may also indicate the presence of contaminating materials, such as water, conducting particles, dissolved contaminants, or the decomposition products resulting from an electric arc. A high dielectric breakdown voltage, however, is not a certain indication of the absence of all contaminants.

3. Flash and Fire Point - D 92

The flash point of askarel is the temperature to which askarel must be heated in order to give off sufficient vapor to form a flammable mixture with air under the conditions of the test. Askarels have a flash point which is not indicative of a hazardous condition unless followed by a fire point.

The fire point of a material that emits combustible vapor may be defined as the temperature to which the material must be heated in order to support continuous combustion when exposed to the atmosphere under prescribed conditions. Askarels have no fire point. The test is only of value, therefore, in showing whether the material has the nonflammable characteristics required of an askarel, or has a large amount of combustible contaminant.

4. Inorganic Chlorides - D 1821

In the presence of water chlorides can ionize. Their corrosive action can then be detrimental to the life of the apparatus in which the askarel is used. The presence of ionizable chlorides may be indicative of arc decomposition of the askarel.

5. Neutralization Number - D 974, D 664

In the inspection of new askarels, the neutralization value is of importance as a quality index of purity.

Since askarel is not subject to deterioration by oxidation, small changes in the neutralization value of service aged askarels may indicate the solution of basic or acidic materials from the various solid materials in contact with the askarel or the deterioration of such soluble materials to form basic or acidic materials. A large change in acidity may indicate decomposition of the askarel by an electric arc.

6. Pour Point - D 97

The pour point of askarel may be defined as the temperature at which the liquid just flows under prescribed conditions of test. The pour point has little significance as far as contamination or deterioration is concerned but may be used for type identification.

MONS 075352

7. Power Factor - D 924, D 150

Power factor is the ratio of the power dissipated in the askarel in watts to the product of the effective voltage and current in volt-amperes, when tested with a sinusoidal field under prescribed conditions. Since askarel is not subject to oxidation, an increase of power factor value of the askarel in service may be attributed to the presence of moisture, dissolved polar compounds or other contaminants. Depending upon the type of apparatus and application, high power factor due to contamination other than moisture seldom impairs the serviceability of the askarel. However, the high power factor may influence the transformer winding power factor.

8. Refractive Index - D 1807

Refractive Index is defined as the ratio of the velocity of light in air to its velocity in the substance under prescribed conditions. The refractive index of askarel varies with its composition and with the nature and amount of contaminants held in solution. Changes of refractive index of askarel in service may be useful in estimating compositional change and degree of soluble contamination.

9. Resistivity (Specific Resistance) - D 1169

Volume resistivity (specific resistance), in ohm-centimeters, of askarel is the ratio of the dc potential gradient in volts per centimeter paralleling the current flow within the sample to the current density in amperes per square centimeter at a given instant of time and under prescribed conditions. The resistivity of askarel is a measure of its electrical insulating properties. High resistivity normally reflects low content of free ions and ion-forming particles and indicates a low concentration of conductive contaminants.

10. Scavenger Content - D 1701

Askarels are decomposed by an electric arc with the evolution of HCl gas. A scavenger, which reacts chemically with dissolved HCl gas to form a nonvolatile reaction product, may be added to an askarel and serves a useful function in improved preservation of the submerged portion of the apparatus should an arc occur. Measurement of scavenger content indicates the amount of protection available against dissolved arc-formed gases and permits estimation of the amount of make-up additive required.

11. Specific Gravity (Relative Density) - D 1810

The specific gravity (relative density) of an askarel is the ratio of the weights of equal volumes of askarel and water at 15.56C (60F). Specific gravity (relative density) may be useful for type identification or to determine marked compositional changes.

MONS 075353

12. Viscosity - D 88, D 445

The viscosity of an askarel is its resistance to uniformly continuous flow, without turbulence, inertia, or other forces, and is usually determined by measuring the time of flow of a given quality of liquid under controlled conditions. Viscosity of askarels varies with temperature, and for that reason is always designated at a specified temperature.

Viscosity is a controlling factor in the dissipation of heat by convection in insulating and cooling liquids. This is particularly important in transformers and other apparatus where heat generated in windings and cores must be largely removed by transmission through the liquid to a heat exchanger or the containing case. It is also a factor in the rate of impregnation of certain apparatus.

13. Visual Examination of Service Aged Askarels In The Field - D 1702

This method provides for field examination of service aged askarels, sampled from equipment in service, chiefly for the purpose of determining whether laboratory tests are required. This method may be of significance in visually detecting cloudiness which is an indication of the presence of moisture, carbon particles, which may show an arcing condition, or color which is chiefly significant as an indicator of contamination in askarels. No definite relationship has been established between color and the physical and electrical characteristics of the liquid. By the use of this method it may be possible to extend the period between routine laboratory tests.

14. Volume of Oil in Oil-Contaminated Askarel - D 1808

The quantitative determination of the volume of oil in oil-contaminated askarel is important as a check on the degree of contamination and as a means of ascertaining when the nonflammable property of this fluid has been impaired to such an extent that it can no longer be classified as a nonflammable liquid.

15. Water Content - D 1533

The water content is that amount of water, expressed in parts per million by weight, which is present in the liquid. The test is significant in that it will show the presence of water which may not be evident from electrical tests. Changes in water content of askarel in service may be indicative of undesirable operating conditions requiring correction.

MONS 075354

VIII TESTING PROCEDURES

The testing of askarels is best accomplished in adequately equipped laboratories. However, some find it advantageous to make "Field Screening Tests".

(A) Field Screening

Field screening tests are usually made to determine which samples of askarel may require laboratory investigation. Since most tests of askarel can be done best with laboratory equipment and trained personnel, field tests are usually limited to visual inspection and dielectric breakdown voltage.

No standardized procedure is available at the present time for performing field tests on service aged askarel or for classification. Portable dielectric test sets have been available for some time and have proved satisfactory. In addition to the above tests, some operators with suitable field equipment and trained personnel may wish to gain additional information by use of a power factor test. In interpreting results of these tests, consideration must be given to other characteristics of the askarel.

(B) Laboratory Screening

Askarel requiring laboratory evaluation will vary widely in condition depending upon the degree of contamination. There are many tests of a research nature which could be applied, but the general use of such tests would be impractical. The following tests, therefore, are believed to be adequate for classifying service aged askarel.

1. Dielectric breakdown voltage
2. Inorganic chlorides
3. Neutralization number
4. Power factor or resistivity (specific resistance)
5. Specific gravity (relative density)
6. Visual condition and color
7. Water content

IX RECONDITIONING AND RECLAIMING SERVICE AGED ASKAREL

A. General

Askarel does not oxidize, sludge, or decompose in normal transformer use. It will break down when subjected to an electrical arc. If the arc exposure has been of long duration, it is usually best to discard the fluid.

MGNS 075355

However, when arc exposure has been relatively mild or if the askarel is merely contaminated with moisture and other conducting impurities, restoration is practical. An exception is the lack of a practical method for removing mineral oil from askarel. Askarel contaminated with over 2% by volume of transformer mineral oil may no longer be classified as a nonflammable liquid.

B. Treatment After Exposure to An Arc

When askarel is exposed to arcing, hydrogen chloride gas is liberated. Some hydrogen chloride will remain dissolved in the askarel, and must be removed as quickly as possible.

This is done by bubbling about 220 cubic feet (6.23 cubic meters) (1 cylinder) of dry nitrogen through each 100 gallons (3.785 cubic meters) of askarel. The nitrogen should be admitted at the bottom of the tank or container vented sufficiently to allow the nitrogen to escape, while preventing entrance of moisture. This procedure for removing hydrogen chloride is recommended even though the askarel contains a hydrogen chloride scavenger.

C. Filtering Through Dry Blotter Paper to Remove Moisture and Extraneous Particles

Since undissolved moisture will be at the surface of the askarel any simple means should be used to drain or siphon off excess water.

The final drying is done by circulating the askarel through dry blotter paper. The askarel temperature should not exceed 60C. Several passes through multiple layers of freshly dried paper may be required. Filtering should not be done when the relative humidity exceeds 75%.

The filter paper must be dried immediately before use. For best results, the paper is spread for maximum surface exposure in a hot air circulating oven and heated for 4 - 6 hours at 110C.

After filtration the dielectric breakdown voltage of the askarel should be at least 35 kV.

D. Fuller's Earth Treatment for Maximum Improvement of Power Factor and Volume-Resistivity

The askarel should be relatively dry prior to final refinement with conditioned fuller's earth.

Most operators prefer a portable fuller's earth refining apparatus such as a plate press or an earthen cartridge type filter. As this apparatus involves recirculation, the askarel should be removed from the top of the tank and returned at the bottom, because free moisture and most of

the other undissolved contaminants will be found near the surface of the askarel. Since these recirculating procedures can introduce air into the askarel, sufficient time (at least 4 hours and preferably over night) should be allowed for the air to escape before re-energizing the apparatus.

When a filter press is used, the plates are fitted with dry filter paper. This is coated with 0.1 to 0.2% by weight of dried fuller's earth based on the weight of askarel to be treated. (Askarel weighs nearly 13 pounds per U. S. gallon.) (1556 Kilograms per cubic meter) The finely divided clay should be activated and dried to not over 1% of moisture by heating for 12 hours in shallow trays at about 200C, immediately prior to use.

To deposit the fuller's earth evenly, about 1/3 of the total quantity is stirred into a small portion of the askarel in a clean container. This mixture is pumped through the filter, then followed with two more 1/3 portions. Then the askarel is pumped from the top level of the tank, through the filter and returned to the tank at the bottom. It is desirable that the askarel temperature not exceed 60C during the filtering operation.

Circulation is continued until the fluid is clear and tests show that the electrical properties are fully restored.

E. Addition of Scavengers

Only slight loss (by selective absorption) of the hydrogen chloride scavengers occurs when askarel is refined by treatment with 0.2% by weight of fuller's earth at a temperature not above 60C. Significant removal of the additives can result from treatment with much larger amounts of fuller's earth.

Initially 0.1 - 0.2% by weight of scavenger, usually an epoxide is incorporated in modern transformer askarel. Inquiries about replenishing the additive should be directed to the transformer manufacturer, or to the supplier of the fluid.

X HANDLING MATERIALS

All common metals are satisfactory for use with askarel in dry environments. To avoid rust, it is preferable to use stainless steel or aluminum for filter presses or equipment used intermittently or in the presence of moisture.

Because stainless steel piping may be difficult to fabricate, the use of aluminum or galvanized steel is more common.

Pipe connections should be welded wherever possible. Flanged connections are very good when fitted with a sufficient number of bolts to hold the gasket seal securely.

MONS 075357

Where readily removable connections are needed, deep pipe threads should be cut and wrapped with Teflon tape to make the seal.

In addition to Teflon, other materials completely compatible with askarel and suitable for gaskets are: Viton and Silastic (silicone) elastomers and Flexitallic stainless steel rings with either Viton, Teflon or silicone elastomer between the steel laminations. Silicone elastomer does not have good abrasive resistance and it is not suitable for use with mineral oil. Viton has relatively good abrasion resistance and is resistant to both askarel and mineral oil.

If a fine grain cork-nitrile rubber composition gasket is used, it is desirable to coat the exterior of the seal with room temperature curing epoxy cement or RTV silicone cement.

Well cured or dried adhesive cements of dewaxed orange shellac, dextrine glue, Elvanol (polyvinyl alcohol acetate), phenolic or epoxy, are relatively noncontaminating to askarel.

Suitable hoses are those of the flexible metal type, or those in which only Teflon or silicone polymers are in contact with the askarel.

The preferred valves are those in which only stainless steel is in contact with the askarel. Where required, the stainless steel valve may be seated with Teflon. Also brass valves are acceptable.

Suitable valve stem packing is the #117 braided Garlock type, or Raybestos Manhattan type 365-C, or any equivalent asbestos graphite packing.

Centrifugal pumps suitable for handling hot oil are the recommended type. Gear type pumps are not desirable. All wetted surfaces of the pump should be of stainless steel. The shaft seal should be the external mechanical (carbon ring) type to eliminate packing material and its exposure to askarel. All askarel handling equipment should be reserved solely for use with askarel, and should not be used interchangeably with mineral oil.

XI ASKAREL USED UNDER MILD ARCING CONDITIONS

Askarel is used, to some extent, in apparatus where it is subjected to light intermittent arcing, such as in self-contained induction regulators, where operating switches are continually producing slight arcs, in transformer deenergizing switches, etc. Under normal operating conditions, deterioration of the askarel is very slight. However, improperly adjusted or defective switches in this type of apparatus can produce excessive and prolonged arcing and accelerated deterioration of the askarel. It is recommended that when askarel is used under these conditions, checks of the liquid, especially for moisture and dielectric strength, be made more frequently than when it is used only as a cooling and insulating fluid. Deterioration of this type is indicated by a blackening of the liquid. It can usually be reconditioned as previously described. Special attention should be given to maintaining the scavenger at the appropriate concentration.

MONS 075358

XII ASKAREL UNDER EXCESSIVE TEMPERATURE OR FAULT CONDITIONS

Chlorobenzenes used in transformer askarels begin to boil at temperatures of about 205C, under atmospheric conditions. If the material is heated to such high temperature in a sealed system, pressure develops. Pressure will also develop in the system if the askarel is arced sufficiently to generate copious hydrogen chloride gas.

Therefore, it is recommended that wherever possible, sealed askarel filled equipment be provided with pressure relief devices. These devices must be large enough to provide immediate relief at a definite pressure, and to prevent further build up of pressure if decomposition continues. It must be remembered that the presence of devices of this sort does not necessarily preclude the rupturing of containing vessels, since pressure build up can be extremely rapid under violent arcing conditions.

XIII RECOMMENDED HANDLING PRECAUTIONS

It is generally accepted that the exposure to askarel is not hazardous, provided simple precautions are taken. Most people can handle askarel in the same manner as insulating oil without fear of adverse effects. Some people are allergic to askarel, and continued exposure may result in skin irritation. Therefore, direct contact with askarel and its vapors, particularly when hot, should be avoided. This combined with personal cleanliness should constitute adequate safeguards against harmful effects. Eye protection (glasses, shields, etc.) are required. The use of any type glove should be avoided. Medicinal washes or detergents followed by an application of cold cream or Silicare have been successfully used to eliminate irritation resulting from askarel coming into contact with an open cut or skin abrasion. A drop of castor oil has been found to neutralize, in most cases, irritation caused by contact of askarel with the eyes.

Exposure to concentrated askarel vapors should be avoided, particularly in closed, unventilated rooms. As with many volatile liquids, the vaporisation of askarel increases rapidly with temperature. Therefore, ventilation which is adequate for handling askarel at room temperature may not be adequate for handling askarel at elevated temperatures. The gases produced when askarel is decomposed by very high temperatures or an electric arc in the presence of air or organic insulating materials, contain a high percentage of hydrogen chloride, and small percentages of carbon dioxide, carbon monoxide and oxygen. Very small concentrations of this combination of gases are very unpleasant and irritating, thus giving ample warning of their presence. The all-purpose canister type gas masks are suitable for protection from gases liberated from decomposed askarel.

XIV STORAGE AND HANDLING

Transformer askarel can be handled in about the same manner as transformer mineral oil.

A. Drums

The askarel drum is made of steel lined with a specially selected material properly cured. Galvanized drums may also be used.

Askarel must be kept dry. It can pick up moisture from contact with humid air. Drums of askarel should not be stored outdoors in an upright position, as water can collect in the dish of the drum head, and can be drawn into the drum under certain conditions. Drums should be stored on their sides with the bungs downward and under cover. It is preferable to store drums indoors.

Askarel should not be transferred into drums that have previously contained other materials.

B. Tank Cars

Tank cars are solid aluminum, or steel lined with aluminum, or a zinc-tin coating.

It is desirable to provide canopies for unloading askarel cars. The car should not be opened in the rain or snow. It is desirable to not open the car if the relative humidity exceeds 75%. Precautions must always be taken to exclude dirt.

C. Sampling

(Please refer to Section VI)

D. Effect of Light Exposure

Prolonged exposure to ultraviolet light (sunlight, some fluorescent lights) should be avoided. Askarel can decompose under such conditions. Sample bottles are preferably of the amber glass type.

E Disposal

XV UNDERWRITERS' LABORATORIES REPORTS

The Underwriters' Laboratories have exhaustively examined, at the electrical manufacturers' requests, the miscellaneous hazards involved in the use of askarel and askarel-filled apparatus. Reports have been issued to the respective manufacturers covering the tradenamed askarels being considered. It is suggested that interested users of transformer askarel contact the manufacturers for this information.

? Methods of disposal are given in ANSI Committee on Guidelines.

MONS 075360

APPENDIX

RESULTS OF SURVEY OF UNITED STATES AND CANADIAN USERS OF TRANSFORMER ASKAREL

I GENERAL

This survey of the United States and Canadian users of askarels was made in 1966 in order to show the practices followed in testing, reconditioning, and reclaiming of askarels. Of the 96 inquiries sent out, 50 replies were received with usable information which is a 52% return. All of the following data are shown as a percentage of those returning the questionnaires and it should be pointed out that this includes information from both manufacturers as well as users and no attempt has been made to classify them according to the size of the systems involved.

Thirty-two percent of the users make only field tests; thirty-two percent make only laboratory tests; twenty-four percent make both field and laboratory tests; and twelve percent make no tests at all on askarels. Most all make tests at a fixed time interval and the largest group follow a yearly schedule. Sixty-seven percent recondition askarel, which is below acceptable limits, and the most popular method employs the combination fuller's earth and blotter press.

This survey was made purposely to determine the types of tests being made by askarel users and to give an indication of acceptable limits. The following data are the over-all results of the questionnaire.

Askarel - Field Tests

Fifty-six percent of askarel users do some type of field testing. Of these 93% make a test for dielectric breakdown voltage.

Fifty-seven percent make at least two field tests:

(a) Dielectric breakdown voltage
(b) Visual examination and color

Other tests used in decreasing order of frequency are power factor, neutralization number and moisture.

Askarel - Laboratory Testing

Fifty-six percent of askarel users make an average of four tests in their laboratories on samples. Of these 93% determine the dielectric breakdown voltage.

MONS 075361

Sixty-four percent make at least four tests:

(a) Dielectric breakdown voltage
(b) Color and condition
(c) Neutralization Number
(d) Moisture content
(e) Power factor

Other tests used in decreasing order of frequency are inorganic chlorides, resistivity (specific resistance) and specific gravity (relative density).

Askarel - New Equipment

Eighty percent of the users test the dielectric breakdown voltage of askarel in new equipment. Twenty-two percent also test:

(a) Power factor
(b) Moisture

Other tests used in decreasing order of frequency are neutralization number, inorganic chlorides and resistivity (specific resistance).

II TESTING

A. 100% of companies reporting tests used askarels and approximately:

1. 32% use only field tests
2. 32% use only laboratory tests
3. 24% use both field and laboratory tests
4. 12% do not test

B. The relative importance of the field tests are as follows:

1. 93% dielectric breakdown voltage
2. 40% color and visual examination
3. 14% power factor
4. 11% neutralization number

C. The average limits on service aged samples are as follows:

1. Dielectric breakdown voltage - Average 27 kV - Range 20-35 kV
2. Power factor - Average 10% - Range 2-40%
3. Neutralization number - Average .12 - Range .05-.5
4. Inorganic chlorides - Average .5 - Range .01-2.0
5. Moisture - Average 45 ppm - Range 40-55 ppm

D. The average limits on askarel in new equipment are as follows:

1. Dielectric breakdown voltage - Average 30 kV - Range 22.5-35 kV
2. Power factor - Average 3% - Range .05-5%
3. Moisture - Average 32.5 ppm - Range 20-50 ppm

MONS 075362

III RECONDITIONING

A. 67% recondition askarel from transformers:

1. 73.5% prefer the combination fuller's earth-blotter press
2. 17.5% use only the blotter press
3. 9% use only fuller's earth

B. The average limits on reconditioned askarels are as follows:

1. Dielectric breakdown voltage - Average 29 kV - Range 23-35 kV
2. Power factor - Average 3.5% - Range 2-15%
3. Neutralization Number - Average .10 - Range .01-.5
4. Moisture - Average 35 ppm - Range 30-50 ppm

IV FREQUENCY OF TESTING

A. The frequency of testing practiced by askarel users is as follows:

1. 53% test every year
2. 17.5% test every five years
3. 17.5% test when there is a reason for testing
4. 9% test every two years
5. 3% test every six months

B. Most users test all askarel units at the same interval regardless of rating.

MCNS 075363