



PANELBOARDS

Convertible Type CDP Circuit Breaker Panelboards

FOR PRICING INSTRUCTIONS,
See Previous Page.

BASE PRICE ①

② Amp. Mains 2, 3 or 4 Wire	Largest Breaker Allowed			Space Req. X—Units
	225 A JA or KA	400 A LA or MA	600 A MA	
225	\$86.	---	---	3X
400	108.	\$140.	---	3X
600	140.	173.	\$208.	5X
800	173.	208.	273.	5X
1200	238.	273.	347.	9X

BRANCH CIRCUITS

Breaker			Price					Space X Units X = 1 1/8"
Frame and Type	Trip Rating	No. of Poles	250V. A-c 125V. D-c	480V. A-c	600V. A-c 250V. D-c	③ Space Only	Provision for Future Breaker	
NON-INTERCHANGEABLE TRIP								
④ 50 Amp.	15, 20, 30, 40, 50 Amp.	1	\$19.50 (E)	\$22. (EH)	---	\$5.50	\$8.	1X
		2	39. (E)	62. (EH)	\$71. (F)	6.50	11.	2X
		3	56. (E)	80. (EH)	92. (F)	8.50	15.	3X
100 Amp. ④	70, 90, 100 Amp.	2	57. (E)	76. (EH)	87. (F)	6.50	11.	2X
		3	75. (E)	94. (EH)	108. (F)	8.50	15.	3X
225 Amp. JA	125, 150, 175, 200, 225 Amp.	2	193.	193.	193.	18.50	28.	4X
		3	242.	242.	242.	18.50	42.	4X
INTERCHANGEABLE TRIP								
225 Amp. KA ④	125, 150, 175, 200, 225 Amp.	2	\$246.	\$246.	\$246.	\$18.50	\$58.	4X
		3	317.	317.	317.	18.50	83.	4X
400 Amp. LA ④ ⑤	250, 300, 350, 400, Amp.	2	368.	368.	368.	18.50	65.	6X
		3	453.	453.	453.	18.50	87.	6X
600 Amp. MA	250, 275, 300, 325, 350, 400, 450, 500, 550, 600 Amp.	2	566.	566.	566.	37.	110.	6X
		3	731.	731.	731.	37.	153.	6X
800 Amp. MA	700, 800 Amp.	2	737.	737.	737.	37.	144.	6X
		3	953.	953.	953.	37.	188.	6X

SPECIFICATIONS

Application: A-c or D-c. Meets Federal Specification W-P-131a. Underwriter's Laboratories listed.

Service: 600 volts A-c, 250 volts D-c, max.
Single phase—2 or 3 wire.
Three phase—3 or 4 wire.

Mains: Lugs only—up to 1200 amperes
Breaker—up to 800 amperes

Standard Terminals CU wire only.
AL-CU Lugs—Information on Application.

Branches: Types E, EH, F, JA, KA, LA and MA breakers.

SOLID NEUTRAL BARS ⑥

Amp.	Price	Space Req. X—Units
225	\$25.	3X
400	32.	3X
600	46.	4X
800	65.	4X
1200	77.	4X

SPLIT BUS-LUGS

Amp.	Price		Space Req. X—Units
	2 Pole	3 Pole	
200	\$46.	\$55.	3X
400	55.	65.	6X
600	65.	72.	6X
800	92.	102.	8X
1200	110.	119.	12X

SUB-FEED LUGS ONLY OR FEED THROUGH LUGS AT BOTH ENDS

Main Amps.	Price	
	2 Bus Bars	3 Bus Bars
225	\$18.	\$24.
400	37.	43.
600	65.	72.
800	92.	102.
1000	110.	120.

① Use once per Breaker panel. Base Price is determined by largest breaker in panel (Main or Branch). Price includes top and bottom gutters, with respective sections of bus, box and front to circuit edge. Remaining equipment for complete Breaker panel included in Branch Circuit Prices.

② For Panelboard with Main Breaker, consider main breaker as branch breaker with main lugs and price accordingly.

③ "Space Only" prices are to be used only when specifications require space for future circuits.

④ KA and LA frame circuit breakers require full width of panel when used as main breakers. No branch breaker may be mounted opposite.

⑤ Price includes neutral bar, lug for each branch circuit, portion of back plate, box and trim.

⑥ E and EH breakers cannot be located opposite F frame breakers.

DISCOUNT SCHEDULE 23 CD

FOR OPTIONS AND SPECIAL FEATURES see next page

CUTLER-HAMMER